National Semiconductor

COP988CF/COP984CF/COP888CF/COP884CF Single-Chip microCMOS Microcontroller

General Description

The COP888 family of microcontrollers uses an 8-bit single chip core architecture fabricated with National Semiconductor's M²CMOSTM process technology. The COP888CF is a member of this expandable 8-bit core processor family of microcontrollers. (Continued)

Features

- Low cost 8-bit microcontroller
- Fully static CMOS, with low current drain
- Two power saving modes: HALT and IDLE
- 1 µs instruction cycle time
- 4096 bytes on-board ROM
- 128 bytes on-board RAM
- Single supply operation: 2.5V-6V
- 8-channel A/D converter with prescaler and both differential and single ended modes
- MICROWIRE/PLUS™ serial I/O
- WATCHDOG[™] and Clock Monitor logic
- Ten multi-source vectored interrupts servicing
 - External Interrupt
 - Idle Timer T0
 - Two Timers (Each with 2 Interrupts)
 - MICROWIRE/PLUS
 - Multi-Input Wake Up
 - Software Trap
 - Default VIS
- Idle Timer

Block Diagram

- Multi-Input Wakeup (MIWU) with optional interrupts (8)
- Two 16-bit timers, each with two 16-bit registers supporting:
- Processor Independent PWM mode
- External Event counter mode
- Input Capture mode
- 8-bit Stack Pointer SP (stack in RAM)
- Two 8-bit Register Indirect Data Memory Pointers (B and X)
- Versatile instruction set
- True bit manipulation
- Memory mapped I/O
- BCD arithmetic instructions
- Package:
 - 44 PLCC with 37 I/O pins
 - 40 N with 33 I/O pins
 - 28 SO or 28 N, each with 23 I/O pins
- Software selectable I/O options
 - TRI-STATE® Output
 - Push-Pull Output
 - Weak Pull Up Input
 - High Impedance Input
- Schmitt trigger inputs on ports G and L
- Temperature ranges: 0°C to +70°C -40°C to + 85°C
- One-Time Programmable (OTP) emulation devices
- Real time emulation and full program debug offered by Metalink's Development Systems



General Description (Continued)

It is a fully static part, fabricated using double-metal silicon gate microCMOS technology. Features include an 8-bit memory mapped architecture, MICROWIRE/PLUS serial I/O, two 16-bit timer/counters supporting three modes (Processor Independent PWM generation, External Event counter, and Input Capture mode capabilities), an 8-channel, 8-bit A/D converter with both differential and single ended modes, and two power savings modes (HALT and

Connection Diagrams

IDLE), both with a multi-sourced wakeup/interrupt capability. This multi-sourced interrupt capability may also be used independent of the HALT or IDLE modes. Each I/O pin has software selectable configurations. The device operates over a voltage range of 2.5V to 6V. High throughput is achieved with an efficient, regular instruction set operating at a maximum of 1 μ s per instruction rate.





Top View

Order Number COP888F-XXX/N See NS Molded Package Number N40A

FIGURE 2. Connection Diagrams

Connection Diagrams (Continued)

Port	Туре	Alt. Fun	Alt. Fun	28-Pin Pack.	40-Pin Pack.	44-Pin Pack.
L0 L1 L2 L3 L4 L5 L6 L7	1/0 1/0 1/0 1/0 1/0 1/0 1/0	MIWU MIWU MIWU MIWU MIWU MIWU MIWU MIWU	T2A T2B	11 12 13 14 15 16 17 18	17 18 19 20 21 22 23 24	
G0 G1 G2 G3 G4 G5 G6 G7	1/0 WDOUT 1/0 1/0 1/0 1 1/0 1 1/CKO	INT T1B T1A SO SK SI HALT Restart		25 26 27 28 1 2 3 4	35 36 37 38 3 4 5 6	39 40 41 42 3 4 5 6
D0 D1 D2 D3	0 0 0 0			19 20 21 22	25 26 27 28	29 30 31 32
10 1 2 3	! 	ACH0 ACH1 ACH2 ACH3		7 8	9 10 11 12	9 10 11 12
4 5 6 7	 	ACH4 ACH5 ACH6 ACH7			13 14	13 14 15 16
D4 D5 D6 D7	0 0 0 0				29 30 31 32	33 34 35 36
C0 C1 C2 C3 C4 C5 C6 C7	1/0 1/0 1/0 1/0 1/0 1/0 1/0 1/0				39 40 1 2	43 44 1 2 21 22 23 24
V _{REF} AGND V _{CC} GND CKI RESET	+ V _{REF} AGND			10 9 6 23 5 24	16 15 8 33 7 34	18 17 8 37 7 38

Pinouts for 28-, 40- and 44-Pin Packages

Absolute Maximum Ratings

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

 Supply Voltage (V_{CC})
 7V

 Voltage at Any Pin
 -0.3V to V_{CC} + 0.3V

 Total Current into V_{CC} Pin (Source)
 100 mA

Total Current out of GND Pin (Sink)

Storage Temperature Range

110 mA -65°C to +140°C

Note: Absolute maximum ratings indicate limits beyond which damage to the device may occur. DC and AC electrical specifications are not ensured when operating the device at absolute maximum ratings.

DC Electrical Characteristics 988CF: 0°C ≤ T_A ≤ +70°C unless otherwise specified

Parameter	Conditions	Min	Тур	Max	Units
Operating Voltage					
988CF		2.5		4.0	v
998CFH		4.0		6.0	<u>v</u>
Power Supply Ripple (Note 1)	Peak-to-Peak			0.1 V _{CC}	V
Supply Current (Note 2)					
CKI = 10 MHz	$V_{CC} = 6V, t_{c} = 1 \ \mu s$		- A.	12.5	mA
CKI = 4 MHz	$V_{\rm CC} = 6V, t_{\rm C} = 2.5 \mu {\rm s}$			5.5	mA
CKI = 4 MHz	$V_{CC} = 4V, t_{c} = 2.5 \mu s$			2.5	mA
CKI = 1 MHz	$V_{\rm CC} = 4V, t_{\rm C} = 10\mu\rm s$			1.4	mA
HALT Current (Note 3)	$V_{CC} = 6V, CKI = 0 MHz$		<0.7	8	μA
	$V_{CC} = 4.0V$, CKI = 0 MHz		<0.3	4	μA
IDLE Current					
CKI = 10 MHz	$V_{CC} = 6V, t_{c} = 1 \ \mu s$			3.5	mA
CKI = 4 MHz	$V_{CC} = 6V, t_c = 2.5 \mu s$			2.5	mA
CKI = 1 MHz	$V_{CC} = 4.0V, t_{c} = 10 \ \mu s$			0.7	mA
Input Levels					
RESET					
Logic High		0.8 V _{CC}		í í	v
Logic Low				0.2 V _{CC}	V
CKI (External and Crystal Osc. Modes)					
Logic High		0.7 V _{CC}			V
Logic Low				0.2 V _{CC}	v
An Other Inputs		071/			v
		0.7 VCC		0.2.1/20	v
				0.2 VCC	
	$v_{CC} = 6v$	-1		+1	μΑ
Input Pullup Current	$v_{\rm CC} = 6v, v_{\rm IN} = 0v$	-40		-250	μΑ
G and L Port Input Hysteresis				0.35 V _{CC}	V
Output Current Levels					
D Outputs					
Source	$V_{\rm CC} = 4V, V_{\rm OH} = 3.3V$	-0.4		(mA
0.1	$V_{\rm CC} = 2.5V, V_{\rm OH} = 1.8V$	-0.2			mA
Sink	$V_{CC} = 4V, V_{OL} = 1V$	10			mA
All Others	$v_{CC} = 2.5 V, v_{OL} = 0.4 V$	2.0			MA
Source (Weak Pull-Un Mode)	$V_{00} = 4V V_{01} = 27V$	10		_ 100	
Source (Weak Full-Op Mode)	$V_{CC} = 25V V_{CU} = 18V$	-25		_33	μA Δ
Source (Push-Pull Mode)	$V_{CC} = 4V V_{CU} = 3.3V$	-04			mA
	$V_{CC} = 2.5V V_{CH} = 1.8V$	-02			mA
Sink (Push-Pull Mode)	$V_{CC} = 4V, V_{C1} = 0.4V$	1.6			mA
($V_{CC} = 2.5V, V_{OI} = 0.4V$	0.7			mA

Note 1: Rate of voltage change must be less then 0.5 V/ms.

Note 2: Supply current is measured after running 2000 cycles with a square wave CKI input, CKO open, inputs at rails and outputs open.

Note 3: The HALT mode will stop CKI from oscillating in the RC and the Crystal configurations. Test conditions: All inputs tied to V_{CC}, L and G0–G5 configured as outputs and set high. The D port set to zero. The A/D is disabled. V_{REF} is tied to AGND (effectively shorting the Reference resistor). The clock monitor is disabled.

•••
0
Ť
ž
8
8
œ
Ω
T
~
O.
×
<u> </u>
τ
e
Ô
4
Ô
¥
~
2
\mathbf{Q}
Ο
Ť
ň
~~
~
×
C)
>
0
õ
\simeq
0
œ
œ
4
0
Ť

Conditions	Min	Тур	Max	Unit
$V_{CC} = 6.0V$	-1	_	+1	μΑ
			45	
			3	mA mA
T _A = 25°C			± 100	mA
500 ns Rise and Fall Time (Min)	2			v
			7	pF
			1000	pF
	Conditions $V_{CC} = 6.0V$ $T_A = 25^{\circ}C$ 500 ns Rise and Fall Time (Min)	ConditionsMin $V_{CC} = 6.0V$ -1 $T_A = 25^{\circ}C$ -1 500 ns Rise and Fall Time (Min)2	ConditionsMinTyp $V_{CC} = 6.0V$ -1 $T_A = 25^{\circ}C$	Conditions Min Typ Max $V_{CC} = 6.0V$ -1 +1 15 3 $T_A = 25^{\circ}C$ ± 100 500 ns Rise and Fall Time (Min) 2 7 1000

Parameter	Conditions	MIN	тур	мах	Units
Resolution				8	Bits
Reference Voltage Input	AGND = 0V	3		Vcc	v
Absolute Accuracy	$V_{REF} = V_{CC}$			±1	LSB
Non-Linearity	V _{REF} = V _{CC} Deviation from the Best Straight Line			± 1/2	LSB
Differential Non-Linearity	V _{REF} = V _{CC}		_	± 1/2	LSB
Input Reference Resistance		1.6		4.8	kΩ
Common Mode Input Range (Note 7)		AGND		VREF	v
DC Common Mode Error				± 1/4	LSB
Off Channel Leakage Current			1		μΑ
On Channel Leakage Current			1		μÂ
A/D Clock Frequency (Note 5)		0.1		1.67	MHz
Conversion Time (Note 4)			12		A/D Clock Cycles

Note 4: Conversion Time includes sample and hold time.

Note 5: See Prescaler description.

Note 6: Pins G6 and RESET are designed with a high voltage input network for factory testing. These pins allow input voltages greater than V_{CC} and the pins will have sink current to V_{CC} when biased at voltages greater than V_{CC} (the pins do not have source current when biased at a voltage below V_{CC}). The effective resistance to V_{CC} is 750 Ω (typical). These two pins will not latch up. The voltage at the pins must be limited to less than 14V.

Note 7: For $V_{IN}(-) \ge V_{IN}(+)$ the digital output code will be 0000 0000. Two on-chip diodes are tied to each analog input. The diodes will forward conduct for analog input voltages below ground or above the V_{CC} supply. Be careful, during testing at low V_{CC} levels (4.5V), as high level analog inputs (5V) can cause this input diode to conduct—especially at elevated temperatures, and cause errors for analog inputs near full-scale. The spec allows 50 mV forward bias of either diode. This means that as long as the analog V_{IN} does not exceed the supply voltage by more than 50 mV, the output code will be correct. To achieve an absolute 0 V_{DC} to 5 V_{DC} input voltage range will therefore require a minimum supply voltage of 4.950 V_{DC} over temperature variations, initial tolerance and loading. The voltage at any analog input should be -0.3V to $V_{CC} + 0.3V$.

AC Electrical Characteristics	$0^{\circ}C \le T_A \le +70^{\circ}C$ unless other	wise specifi	ed		
Parameter	Conditions	Min	Тур	Max	Units
Instruction Cycle Time (t _c)					
Crystal, Resonator	$4V \le V_{CC} \le 6V$	1		DC	μs
	$2.5V \leq V_{CC} < 4V$	2.5		DC	μs
R/C Oscillator	$4V \le V_{CC} \le 6V$	3		DC	μs
	$2.5V \le V_{CC} < 4V$	7.5		DC	μs
Inputs			-*		
^t SETUP	$4V \le V_{CC} \le 6V$	200			ns
	$2.5V \le V_{CC} \le 4V$	500			ns
thold	$4V \le V_{CC} \le 6V$	60			ns
	$2.5V \le V_{CC} \le 4V$	150			ns
Output Propagation Delay (Note 8)	$R_{L} = 2.2k, C_{L} = 100 pF$				
tPD1, tPD0					
SO, SK	$4V \le V_{CC} \le 6V$			0.7	μs
	$2.5V \leq V_{CC} < 4V$)		1.75	μs
All Others	$4V \leq V_{CC} \leq 6V$	[1	μs
	$2.5V \le V_{CC} < 4V$	- 10		2.5	μs
MICROWIRE™ Setup Time (t _{UWS})		20			ns
MICROWIRE Hold Time (tUWH)		56			ns
MICROWIRE Output Propagation Delay (tupp)				220	ns
Input Pulse Width					
Interrupt Input High Time		1 1			to
Interrupt Input Low Time		1			t _c
Timer Input High Time		1			tc
Timer Input Low Time		1			t _c
Reset Pulse Width		1			μs

Note 8: The output propagation delay is referenced to the end of the instruction cycle where the output change occurs.



FIGURE 3. MICROWIRE/PLUS Timing

TL/DD/9425-26

Absolute Maximum Ratings

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

 Supply Voltage (V_{CC})
 7V

 Voltage at Any Pin
 -0.3V to V_{CC} + 0.3V

 Total Current into V_{CC} Pin (Source)
 100 mA

Total Current out of GND Pin (Sink)

Storage Temperature Range

- 65°C to + 140°C

110 mA

Note: Absolute maximum ratings indicate limits beyond which damage to the device may occur. DC and AC electrical specifications are not ensured when operating the device at absolute maximum ratings.

DC Electrical Characteristics 888CF: $-40^{\circ}C \le T_A \le +85^{\circ}C$ unless otherwise specified

Parameter	Conditions	Min	Тур	Max	Units
Operating Voltage		2.5		6	v
Power Supply Ripple (Note 1)	Peak-to-Peak			0.1 V _{CC}	v
Supply Current (Note 2) CKI = 10 MHz CKI = 4 MHz	$V_{CC} = 6V, t_c = 1 \ \mu s$ $V_{CC} = 4V, t_c = 2.5 \ \mu s$			12.5 2.5	mA mA
HALT Current (Note 3)	$V_{CC} = 6V, CKI = 0 MHz$		<1	10	μΑ
IDLE Current CKI = 10 MHz CKI = 1 MHz	$V_{CC} = 6V, t_c = 1 \ \mu s$ $V_{CC} = 4V, t_c = 10 \ \mu s$			3.5 0.7	mA mA
Input Levels RESET Logic High Logic Low CKI (External and Crystal Osc. Modes) Logic High Logic Low All Other Inputs Logic High	÷	0.8 V _{CC} 0.7 V _{CC} 0.7 V _{CC}		0.2 V _{CC} 0.2 V _{CC}	> > > >
Logic Low			L	0.2 V _{CC}	V
Hi-Z Input Leakage	$V_{CC} = 6V$	-2		+2	μΑ
Input Pullup Current	$V_{CC} = 6V, V_{IN} = 0V$	- 40		- 250	μA
G and L Port Input Hysteresis				0.35 V _{CC}	V
Output Current Levels D Outputs Source Sink All Others	$\begin{split} v_{CC} &= 4V, v_{OH} = 3.3V \\ v_{CC} &= 2.5V, v_{OH} = 1.8V \\ v_{CC} &= 4V, v_{OL} = 1V \\ v_{CC} &= 2.5V, v_{OL} = 0.4V \end{split}$	-0.4 -0.2 10 2.0			mA mA mA
Source (Weak Pull-Up Mode)	$V_{CC} = 4V, V_{OH} = 2.7V$	- 10		- 100	μΑ
Source (Push-Pull Mode) Sink (Push-Pull Mode)	$V_{CC} = 2.5V, V_{OH} = 1.8V$ $V_{CC} = 4V, V_{OH} = 3.3V$ $V_{CC} = 2.5V, V_{OH} = 1.8V$ $V_{CC} = 4V, V_{OL} = 0.4V$ $V_{CC} = 2.5V, V_{OH} = 0.4V$	-2.5 -0.4 -0.2 1.6 0.7	÷	-33	μA mA mA mA mA
TRI-STATE Leakage	$V_{CC} = 6.0V$	-2		+2	μA

Note 1: Rate of voltage change must be less then 0.5 V/ms.

Note 2: Supply current is measured after running 2000 cycles with a square wave CKI input, CKO open, inputs at rails and outputs open.

Note 3: The HALT mode will stop CKI from oscillating in the RC and the Crystal configurations. Test conditions: All inputs tied to V_{CC}, L and G0–G5 configured as outputs and set high. The D port set to zero. The A/D is disabled. V_{REF} is tied to AGND (effectively shorting the Reference resistor). The clock monitor is disabled.

Parameter	Conditions	Min	Тур	Max	Units
Allowable Sink/Source Current per Pin					
D Outputs (Sink)				15	mA
All others				3	mA
Maximum Input Current without Latchup (Note 6)	T _A = 25°C			±100	mA
RAM Retention Voltage, V _r	500 ns Rise and Fall Time (Min)	2			v
Input Capacitance	4			7	pF
Load Capacitance on D2				1000	pF

A/D Converter Specifications 888CF: $V_{CC} = 5V \pm 10\% (V_{SS} - 0.050V) \le Any Input \le (V_{CC} + 0.050V)$

Parameter	Conditions	Min	Тур	Max	Units
Resolution				8	Bits
Reference Voltage Input	AGND = 0V	3		V _{CC}	v
Absolute Accuracy	$V_{REF} = V_{CC}$			±1	LSB
Non-Linearity	V _{REF} = V _{CC} Deviation from the Best Straight Line			± 1⁄2	LSB
Differential Non-Linearity	$V_{REF} = V_{CC}$			± 1/2	LSB
Input Reference Resistance		1.6		4.8	kΩ
Common Mode Input Range (Note 7)		AGND		VREF	v
DC Common Mode Error				± 1⁄4	LSB
Off Channel Leakage Current			1		μΑ
On Channel Leakage Current			1		μА
A/D Clock Frequency (Note 5)		0.1		1.67	MHz
Conversion Time (Note 4)			12		A/D Clock Cycles

Note 4: Conversion Time includes sample and hold time.

Note 5: See Prescaler description.

Note 6: Pins G6 and RESET are designed with a high voltage input network for factory testing. These pins allow input voltages greater than V_{CC} and the pins will have sink current to V_{CC} when biased at voltages greater than V_{CC} (the pins do not have source current when biased at a voltage below V_{CC}). The effective resistance to V_{CC} is 750Ω (typical). These two pins will not latch up. The voltage at the pins must be limited to less than 14V.

Note 7: For V_{IN}(−)≥ V_{IN}(+) the digital output code will be 0000 0000. Two on-chip diodes are tied to each analog input. The diodes will forward conduct for analog input voltages below ground or above the V_{CC} supply. Be careful, during testing at low V_{CC} levels (4.5V), as high level analog inputs (5V) can cause this input diode to conduct-especially at elevated temperatures, and cause errors for analog inputs near full-scale. The spec allows 50 mV forward bias of either diode. This means that as long as the analog V_{IN} does not exceed the supply voltage by more than 50 mV, the output code will be correct. To achieve an absolute 0 V_{DC} to 5 V_{DC} input voltage range will therefore require a minimum supply voltage of 4.950 V_{DC} over temperature variations, initial tolerance and loading. The voltage on any analog input should be -0.3V to V_{CC} + 0.3V.

Parameter	Conditions	Min	Тур	Max	Units
Instruction Cycle Time (t _c)					
Crystal, Resonator	$4V \le V_{CC} \le 6V$	1		DC	μs
	$2.5V \leq V_{CC} < 4V$	2.5		DC	μs
R/C Oscillator	$4V \le V_{CC} \le 6V$	3		DC	μs
	$2.5V \leq V_{CC} < 4V$	7.5		DC	μs
Inputs					
^t SETUP	$4V \leq V_{CC} \leq 6V$	200			ns
	$2.5V \le V_{CC} \le 4V$	500			ns
t _{HOLD}	$4V \le V_{CC} \le 6V$	60			ns
	$2.5V \le V_{CC} < 4V$	150			ns
Output Propagation Delay (Note 8)	R _L = 2.2k, C _L = 100 pF				
tPD1, tPD0					
SO, SK	$4V \le V_{CC} \le 6V$			0.7	μs
	$2.5V \le V_{CC} \le 4V$			1.75	μs
All Others	$4V \le V_{CC} \le 6V$			1	μs
	$2.5V \leq V_{CC} \leq 4V$			2.5	μs
MICROWIRE™ Setup Time (t _{UWS})		20			ns
MICROWIRE Hold Time (tUWH)		56			ns
MICROWIRE Output Propagation Delay (tUPD)				220	ns
Input Pulse Width					
Interrupt Input High Time		1			tc
Interrupt Input Low Time		1			t _c
Timer Input High Time		1			t _c
Timer Input Low Time		1			t _c
Denet Duly a MA/E-Mile		1 .			

Note 8: The output propagation delay is referenced to end of the instruction cycle where the output change occurs.



FIGURE 3. MICROWIRE/PLUS Timing

TL/DD/9425-26



5.5

5 6

= 4.5

3

6.01

= 4.51

4.5

TL/DD/9425-36

3.5

TL/DD/9425-34

6

TL/DD/9425-30

TL/DD/9425-32

1-210

Pin Descriptions

V_{CC} and GND are the power supply pins.

 $V_{\mbox{\scriptsize REF}}$ and AGND are the reference voltage pins for the onboard A/D converter.

CKI is the clock input. This can come from an R/C generated oscillator, or a crystal oscillator (in conjunction with CKO). See Oscillator Description section.

RESET is the master reset input. See Reset Description section.

The device contains three bidirectional 8-bit I/O ports (C, G and L), where each individual bit may be independently configured as an input (Schmitt trigger inputs on ports G and L), output or TRI-STATE under program control. Three data memory address locations are allocated for each of these I/O ports. Each I/O port has two associated 8-bit memory mapped registers, the CONFIGURATION register and the output DATA register. A memory mapped address is also reserved for the input pins of each I/O port. (See the memory map for the various addresses associated with the I/O ports.) *Figure 4* shows the I/O port configurations. The DATA and CONFIGURATION registers allow for each port bit to be individually configured under software control as shown below:

CONFIGURATION Register	DATA Register	Port Set-Up
0	0	Hi-Z Input (TRI-STATE Output)
0	1	Input with Weak Pull-Up
1	0	Push-Pull Zero Output
1	1	Push-Pull One Output



FIGURE 4. I/O Port Configurations

PORT L is an 8-bit I/O port. All L-pins have Schmitt triggers on the inputs.

Port L supports Multi-Input Wakeup (MIWU) on all eight pins. L4 and L5 are used for the timer input functions T2A and T2B. L0 and L1 are not available on the 44-pin version of the device, since they are replaced by V_{REF} and AGND. L0 and L1 are not terminated on the 44-pin version. Consequently, reading L0 or L1 as inputs will return unreliable data with the 44-pin package, so this data should be masked out with user software when the L port is read for input data. It is recommended that the pins be configured as outputs. Port L has the following alternate features:

- LO MIWU
- L1 MIWU
- L2 MIWU
- L3 MIWU
- L4 MIWU or T2A
- L5 MIWU or T2B
- L6 MIWU
- L7 MIWU

Port G is an 8-bit port with 5 I/O pins (G0, G2–G5), an input pin (G6), and two dedicated output pins (G1 and G7). Pins G0 and G2–G6 all have Schmitt Triggers on their inputs. Pin G1 serves as the dedicated WDOUT WatchDog output, while pin G7 is either input or output depending on the oscillator mask option selected. With the crystal oscillator option selected, G7 serves as the dedicated output pin for the CKO clock output. With the single-pin R/C oscillator mask option selected, G7 serves as a general purpose input pin, but is also used to bring the device out of HALT mode with a low to high transition on G7. There are two registers associated with the G Port, a data register and a configuration register. Therefore, each of the 5 I/O bits (G0, G2–G5) can be individually configured under software control.

Since G6 is an input only pin and G7 is the dedicated CKO clock output pin or general purpose input (R/C clock configuration), the associated bits in the data and configuration registers for G6 and G7 are used for special purpose functions as outlined below. Reading the G6 and G7 data bits will return zeros.

Note that the chip will be placed in the HALT mode by writing a "1" to bit 7 of the Port G Data Register. Similarly the chip will be placed in the IDLE mode by writing a "1" to bit 6 of the Port G Data Register.

Writing a "1" to bit 6 of the Port G Configuration Register enables the MICROWIRE/PLUS to operate with the alternate phase of the SK clock. The G7 configuration bit, if set high, enables the clock start up delay after HALT when the R/C clock configuration is used.

	Config Reg.	Data Reg.
G7	CLKDLY	HALT
G6	Alternate SK	IDLE

Port G has the following alternate features:

- G0 INTR (External Interrupt Input)
- G2 T1B (Timer T1 Capture Input)
- G3 T1A (Timer T1 I/O)
- G4 SO (MICROWIRE Serial Data Output)
- G5 SK (MICROWIRE Serial Clock)
- G6 SI (MICROWIRE Serial Data Input)

Port G has the following dedicated functions:

- G1 WDOUT WatchDog and/or Clock Monitor dedicated output
- G7 CKO Oscillator dedicated output or general purpose input

Port C is an 8-bit I/O port. The 40-pin device does not have a full complement of Port C pins. The unavailable pins are not terminated. A read operation for these unterminated pins will return unpredictable values.

Pin Descriptions (Continued)

Port I is an 8-bit Hi-Z input port, and also provides the analog inputs to the A/D converter. The 28-pin device does not have a full complement of Port I pins. The unavailable pins are not terminated (i.e. they are floating). A read operation from these unterminated pins will return unpredictable values. The user should ensure that the software takes this into account by either masking out these inputs, or else restricting the accesses to bit operations only. If unterminated, Port I pins will draw power only when addressed.

Port D is an 8-bit output port that is preset high when RESET goes low. The user can tie two or more D port outputs (except D2) together in order to get a higher drive.

Note: Care must be exercised with the D2 pin operation. At RESET, the external loads on this pin must ensure that the output voltages stay above 0.8 V_{CC} to prevent the chip from entering special modes. Also keep the external loading on D2 to less than 1000 pF.

Functional Description

The architecture of the device is modified Harvard architecture. With the Harvard architecture, the control store program memory (ROM) is separated from the data store memory (RAM). Both ROM and RAM have their own separate addressing space with separate address buses. The architecture, though based on Harvard architecture, permits transfer of data from ROM to RAM.

CPU REGISTERS

The CPU can do an 8-bit addition, subtraction, logical or shift operation in one instruction (t_c) cycle time.

There are five CPU registers:

A is the 8-bit Accumulator Register

PC is the 15-bit Program Counter Register

PU is the upper 7 bits of the program counter (PC)

PL is the lower 8 bits of the program counter (PC)

B is an 8-bit RAM address pointer, which can be optionally post auto incremented or decremented.

X is an 8-bit alternate RAM address pointer, which can be optionally post auto incremented or decremented.

SP is the 8-bit stack pointer, which points to the subroutine/ interrupt stack (in RAM). The SP is initialized to RAM address 06F with reset.

All the CPU registers are memory mapped with the exception of the Accumulator (A) and the Program Counter (PC).

PROGRAM MEMORY

Program memory consists of 4096 bytes of ROM. These bytes may hold program instructions or constant data (data tables for the LAID instruction, jump vectors for the JID instruction, and interrupt vectors for the VIS instruction). The program memory is addressed by the 15-bit program counter (PC). All interrupts vector to program memory location OFF Hex.

DATA MEMORY

The data memory address space includes the on-chip RAM and data registers, the I/O registers (Configuration, Data and Pin), the control registers, the MICROWIRE/PLUS SIO shift register, and the various registers, and counters associated with the timers (with the exception of the IDLE timer). Data memory is addressed directly by the instruction or indirectly by the B, X and SP pointers. The device has 128 bytes of RAM. Sixteen bytes of RAM are mapped as "registers" at addresses 0F0 to 0FF Hex. These registers can be loaded immediately, and also decremented and tested with the DRSZ (decrement register and skip if zero) instruction. The memory pointer registers X, SP, and B are memory mapped into this space at address locations 0FC to 0FE Hex respectively, with the other registers al usage.

The instruction set permits any bit in memory to be set, reset or tested. All I/O and registers (except A and PC) are memory mapped; therefore, I/O bits and register bits can be directly and individually set, reset and tested. The accumulator (A) bits can also be directly and individually tested. Note: RAM contents are undefined upon power-up.

Reset

The RESET input when pulled low initializes the microcontroller. Initialization will occur whenever the RESET input is pulled low. Upon initialization, the data and configuration registers for Ports L, G, and C are cleared, resulting in these Ports being initialized to the TRI-STATE mode. Pin G1 of the G Port is an exception (as noted below) since pin G1 is dedicated as the WatchDog and/or Clock Monitor error output pin. Port D is initialized high with RESET. The PC, PSW, CNTRL, ICNTRL, and T2CNTRL control registers are cleared. The Multi-Input Wakeup registers WKEN, WKEDG, and WKPND are cleared. The A/D control register ENAD is cleared, resulting in the ADC being powered down initially. The Stack Pointer, SP, is initialized to 06F Hex.

The device comes out of reset with both the WatchDog logic and the Clock Monitor detector armed, and with both the WatchDog service window bits set and the Clock Monitor bit set. The WatchDog and Clock Monitor detector circuits are inhibited during reset. The WatchDog service window of 64k t_c clock cycles. The Clock Monitor bit is initialized to the maximum WatchDog service window of 64k t_c clock cycles. The Clock Monitor bit is initialized high, and will cause a Clock Monitor error following reset if the clock has not reached the minimum specified frequency at the termination of reset. A Clock Monitor error will cause an active low error output on pin G1. This error output will continue until 16-32 t_c clock cycles following the clock frequence of 1 output will enter the TRI-STATE mode.

The external RC network shown in *Figure 5* should be used to ensure that the **RESET** pin is held low until the power supply to the chip stabilizes.



RC > 5 × Power Supply Rise Time FIGURE 5. Recommended Reset Circuit

Oscillator Circuits

The chip can be driven by a clock input on the CKI input pin which can be between DC and 10 MHz. The CKO output clock is on pin G7 (crystal configuration). The CKI input frequency is divided down by 10 to produce the instruction cycle clock $(1/t_c)$.

Figure 6 shows the Crystal and R/C diagrams.

CRYSTAL OSCILLATOR

CKI and CKO can be connected to make a closed loop crystal (or resonator) controlled oscillator.

Table A shows the component values required for various standard crystal values.

R/C OSCILLATOR

By selecting CKI as a single pin oscillator input, a single pin R/C oscillator circuit can be connected to it. CKO is available as a general purpose input, and/or HALT restart pin.

Table B shows the variation in the oscillator frequencies as functions of the component (R and C) values.



FIGURE 6. Crystal and R/C Oscillator Diagrams

TABL	TABLE A. Crystal Oscillator Configuration, $T_A = 25^{\circ}C$								
R1 (kΩ)	R2 (ΜΩ)	C1 (pF)	C2 (րF)	CKI Freq (MH7)	Conditions				
0	1	30	30-36	10	$V_{\rm CC} = 5V$				
0	1	30	30-36	4	$V_{\rm CC} = 5V$				
0	1	200	100-150	0.455	$V_{CC} = 5V$				

TABLE B. R/C Oscillator Configuration, $T_A = 25^{\circ}C$

Β (kΩ)	С (pF)	CKI Freq (MHz)	Instr. Cycle (μs)	Conditions
3.3	82	2.2 to 2.7	3.7 to 4.6	$V_{CC} = 5V$
5.6	100	1.1 to 1.3	7.4 to 9.0	$V_{CC} = 5V$
6.8	100	0.9 to 1.1	8.8 to 10.8	$V_{CC} = 5V$

Note: $3k \leq R \leq 200k$

50 pF \leq C \leq 200 pF

Current Drain

The total current drain of the chip depends on:

- 1. Oscillator operation mode-I1
- 2. Internal switching current-I2
- 3. Internal leakage current-13
- 4. Output source current-I4
- 5. DC current caused by external input not at V_{CC} or GND—I5

- 6. DC reference current contribution from the A/D converter—16
- 7. Clock Monitor current when enabled-17

Thus the total current drain, It, is given as

$$It = |1 + |2 + |3 + |4 + |5 + |6 + |7$$

To reduce the total current drain, each of the above components must be minimum.

The chip will draw more current as the CKI input frequency increases up to the maximum 10 MHz value. Operating with a crystal network will draw more current than an external square-wave. Switching current, governed by the equation, can be reduced by lowering voltage and frequency. Leakage current can be reduced by lowering voltage and temperature. The other two items can be reduced by carefully designing the end-user's system.

$$I2 = C \times V \times f$$

where C = equivalent capacitance of the chip V = operating voltage

f = CKI frequency

Control Registers

CNTRL Register (Address X'00EE)

The Timer1 (T1) and MICROWIRE/PLUS control register contains the following bits:

SL1 & SL0	Select	the	MIC	ROW	/IRE/P	LUS	clock	divide
	by (00	- 2	, 01	= 4,	1x =	8)		

External interrupt edge polarity select ($0 = Rising edge, 1 = Falling edge)$				
Selects G5 and G4 as MICROWIRE/PLUS signals SK and SO respectively				
70 Timer T1 Start/Stop control in timer modes 1 and 2				
Timer T1 Underflow Interrupt Pending Flag in timer mode 3				
Timer T1 mode control bit				
Timer T1 mode control bit				
Timer T1 mode control bit				
T1C2 T1C1 T1C0 MSEL IEDG SL1 SL0				
Bit 0				

PSW Register (Address X'00EF)

The PSW register contains the following select bits:

- GIE Global interrupt enable (enables interrupts)
- EXEN Enable external interrupt
- BUSY MICROWIRE/PLUS busy shifting flag
- EXPND External interrupt pending
- T1ENA Timer T1 Interrupt Enable for Timer Underflow or T1A Input capture edge
- T1PNDA Timer T1 Interrupt Pending Flag (Autoreload RA in mode 1, T1 Underflow in Mode 2, T1A capture edge in mode 3)
- C Carry Flag
- HC Half Carry Flag

	нс	С	T1PNDA	T1ENA	EXPND	BUSY	EXEN	GIE
--	----	---	--------	-------	-------	------	------	-----

Bit 7

Control Registers (Continued)

The Half-Carry bit is also affected by all the instructions that affect the Carry flag. The SC (Set Carry) and RC (Reset Carry) instructions will respectively set or clear both the carry flags. In addition to the SC and RC instructions, ADC, SUBC, RRC and RLC instructions affect the carry and Half Carry flags.

ICNTRL Register (Address X'00E8)

The ICNTRL register contains the following bits:

- T1ENB Timer T1 Interrupt Enable for T1B Input capture edge
- T1PNDB Timer T1 Interrupt Pending Flag for T1B capture edge
- μWEN Enable MICROWIRE/PLUS interrupt
- µWPND MICROWIRE/PLUS interrupt pending
- T0EN Timer T0 Interrupt Enable (Bit 12 toggle)
- TOPND Timer TO Interrupt pending
- LPEN L Port Interrupt Enable (Multi-Input Wakeup/Interrupt)

Bit 7 could be used as a flag

Unused	LPEN	TOPND	TOEN	μWPND	μWEN	T1PNDB	T1ENB
Bit 7							Bit 0

T2CNTRL Register (Address X'00C6)

The T2CNTRL register contains the following bits:

- T2ENB Timer T2 Interrupt Enable for T2B Input capture edge
- T2PNDB Timer T2 Interrupt Pending Flag for T2B capture edge
- T2ENA Timer T2 Interrupt Enable for Timer Underflow or T2A Input capture edge
- T2PNDA Timer T2 Interrupt Pending Flag (Autoreload RA in mode 1, T2 Underflow in mode 2, T2A capture edge in mode 3)
- T2C0 Timer T2 Start/Stop control in timer modes 1 and 2 Timer T2 Underflow Interrupt Pending Flag in timer mode 3
- T2C1 Timer T2 mode control bit
- T2C2 Timer T2 mode control bit
- T2C3 Timer T2 mode control bit

T2C3	T2C2	T2C1	T2C0	T2PNDA	T2ENA	T2PNDB	T2ENB
Bit 7							Bit 0

Timers

The device contains a very versatile set of timers (T0, T1, T2). All timers and associated autoreload/capture registers power up containing random data.

Figure 7 shows a block diagram for the timers.

TIMER TO (IDLE TIMER)

The device supports applications that require maintaining real time and low power with the IDLE mode. This IDLE mode support is furnished by the IDLE timer T0, which is a 16-bit timer. The Timer T0 runs continuously at the fixed rate of the instruction cycle clock, t_c . The user cannot read or write to the IDLE Timer T0, which is a count down timer.

The Timer T0 supports the following functions:

Exit out of the Idle Mode (See Idle Mode description) WatchDog logic (See WatchDog description) Start up delay out of the HALT mode

The IDLE Timer T0 can generate an interrupt when the thirteenth bit toggles. This toggle is latched into the T0PND pending flag, and will occur every 4 ms at the maximum clock frequency ($t_c = 1 \mu_s$). A control flag T0EN allows the interrupt from the thirteenth bit of Timer T0 to be enabled or disabled. Setting T0EN will enable the interrupt, while resetting it will disable the interrupt.

TIMER T1 AND TIMER T2

The device has a set of two powerful timer/counter blocks, T1 and T2. The associated features and functioning of a timer block are described by referring to the timer block Tx. Since the two timer blocks, T1 and T2, are identical, all comments are equally applicable to either timer block.

Each timer block consists of a 16-bit timer, Tx, and two supporting 16-bit autoreload/capture registers, RxA and RxB. Each timer block has two pins associated with it, TxA and TxB. The pin TxA supports I/O required by the timer block, while the pin TxB is an input to the timer block. The powerful and flexible timer block allows the device to



FIGURE 7. Timers

easily perform all timer functions with minimal software overhead. The timer block has three operating modes: Processor Independent PWM mode, External Event Counter mode, and Input Capture mode.

The control bits TxC3, TxC2, and TxC1 allow selection of the different modes of operation.

Timers (Continued)

Mode 1. Processor Independent PWM Mode

As the name suggests, this mode allows the COP888CF to generate a PWM signal with very minimal user intervention. The user only has to define the parameters of the PWM signal (ON time and OFF time). Once begun, the timer block will continuously generate the PWM signal completely independent of the microcontroller. The user software services the timer block only when the PWM parameters require updating.

In this mode the timer Tx counts down at a fixed rate of t_c . Upon every underflow the timer is alternately reloaded with the contents of supporting registers, RxA and RxB. The very first underflow of the timer causes the timer to reload from the register RxA. Subsequent underflows cause the timer to be reloaded from the registers alternately beginning with the register RxB.

The Tx Timer control bits, TxC3, TxC2 and TxC1 set up the timer for PWM mode operation.

Figure 8 shows a block diagram of the timer in PWM mode.

The underflows can be programmed to toggle the TxA output pin. The underflows can also be programmed to generate interrupts.

Underflows from the timer are alternately latched into two pending flags, TxPNDA and TxPNDB. The user must reset these pending flags under software control. Two control enable flags, TxENA and TxENB, allow the interrupts from the timer underflow to be enabled or disabled. Setting the timer enable flag TxENA will cause an interrupt when a timer underflow causes the RxA register to be reloaded into the timer. Setting the timer enable flag TxENB will cause an interrupt when a timer underflow causes the RxB register to be reloaded into the timer. Resetting the timer enable flags will disable the associated interrupts.

Either or both of the timer underflow interrupts may be enabled. This gives the user the flexibility of interrupting once per PWM period on either the rising or falling edge of the PWM output. Alternatively, the user may choose to interrupt on both edges of the PWM output.



FIGURE 8. Timer in PWM Mode

Mode 2. External Event Counter Mode

This mode is quite similar to the processor independent PWM mode described above. The main difference is that the timer, Tx, is clocked by the input signal from the TxA pin. The Tx timer control bits, TxC3, TxC2 and TxC1 allow the

timer to be clocked either on a positive or negative edge from the TxA pin. Underflows from the timer are latched into the TxPNDA pending flag. Setting the TxENA control flag will cause an interrupt when the timer underflows.

In this mode the input pin TxB can be used as an independent positive edge sensitive interrupt input if the TxENB control flag is set. The occurrence of a positive edge on the TxB input pin is latched into the TxPNDB flag.

Figure 9 shows a block diagram of the timer in External Event Counter mode.

Note: The PWM output is not available in this mode since the TxA pin is being used as the counter input clock.



FIGURE 9. Timer in External Event Counter Mode

Mode 3. Input Capture Mode

The device can precisely measure external frequencies or time external events by placing the timer block, Tx, in the input capture mode.

In this mode, the timer Tx is constantly running at the fixed t_c rate. The two registers, RxA and RxB, act as capture registers. Each register acts in conjunction with a pin. The register RxA acts in conjunction with the TxA pin and the register RxB acts in conjunction with the TxB pin.

The timer value gets copied over into the register when a trigger event occurs on its corresponding pin. Control bits, TxC3, TxC2 and TxC1, allow the trigger events to be specified either as a positive or a negative edge. The trigger condition for each input pin can be specified independently.

The trigger conditions can also be programmed to generate interrupts. The occurrence of the specified trigger condition on the TxA and TxB pins will be respectively latched into the pending flags, TxPNDA and TxPNDB. The control flag TxE-NA allows the interrupt on TxA to be either enabled or disabled. Setting the TxENA flag enables interrupts to be generated when the selected trigger condition occurs on the TxA pin. Similarly, the flag TxENB controls the interrupts from the TxB pin.

Underflows from the timer can also be programmed to generate interrupts. Underflows are latched into the timer TxC0 pending flag (the TxC0 control bit serves as the timer underflow interrupt pending flag in the Input Capture mode). Consequently, the TxC0 control bit should be reset when entering the Input Capture mode. The timer underflow interrupt is enabled with the TxENA control flag. When a TxA interrupt occurs in the Input Capture mode, the user must check both

Timers (Continued)

whether a TxA input capture or a timer underflow (or both) caused the interrupt.

Figure 10 shows a block diagram of the timer in Input Capture mode.



FIGURE 10. Timer in Input Capture Mode

TIMER CONTROL FLAGS

The timers T1 and T2 have indentical control structures. The control bits and their functions are summarized below.

- Timer Start/Stop control in Modes 1 and 2 TxC0 (Processor Independent PWM and External Event Counter), where 1 =Start, 0 =Stop Timer Underflow Interrupt Pending Flag in Mode 3 (Input Capture)
- **TxPNDA Timer Interrupt Pending Flag**
- **TxPNDB** Timer Interrupt Pending Flag TxENA Timer Interrupt Enable Flag Timer Interrupt Enable Flag TxENB 1 = Timer Interrupt Enabled 0 = Timer Interrupt Disabled
- TxC3 Timer mode control
- TxC2 Timer mode control
- TxC1 Timer mode control

TxC3	TxC2	TxC1	Timer Mode	Interrupt A Source	Interrupt B Source	Timer Counts On
0	0	0	MODE 2 (External Event Counter)	Timer Underflow	Pos. TxB Edge	TxA Pos. Edge
0	0	1	MODE 2 (External Event Counter)	Timer Underflow	Pos. TxB Edge	TxA Neg. Edge
1	0	1	MODE 1 (PWM) TxA Toggle	Autoreload RA	Autoreload RB	tc
1	0	0	MODE 1 (PWM) No TxA Toggle	Autoreload RA	Autoreload RB	tc
0	1	0	MODE 3 (Capture) Captures: TxA Pos. Edge TxB Pos. Edge	Pos. TxA Edge or Timer Underflow	Pos. TxB Edge	tc
1	1	0	MODE 3 (Capture) Captures: TxA Pos. Edge TxB Neg. Edge	Pos. TxA Edge or Timer Underflow	Neg. TxB Edge	tc
0	1	1	MODE 3 (Capture) Captures: TxA Neg. Edge TxB Pos. Edge	Neg. TxB Edge or Timer Underflow	Pos. TxB Edge	tc
1	1	1	MODE 3 (Capture) Captures: TxA Neg. Edge TxB Neg. Edge	Neg. TxA Edge or Timer Underflow	Neg. TxB Edge	t _c

The timer mode control hits (TyC3, TyC2 and TyC1) are detailed below:

Power Save Modes

The device offers the user two power save modes of operation: HALT and IDLE. In the HALT mode, all microcontroller activities are stopped. In the IDLE mode, the on-board oscillator circuitry and timer TO are active but all other microcontroller activities are stopped. In either mode, all on-board RAM, registers, I/O states, and timers (with the exception of TO) are unaltered.

HALT MODE

The device is placed in the HALT mode by writing a "1" to the HALT flag (G7 data bit). All microcontroller activities, including the clock, timers, and A/D converter, are stopped. The WatchDog logic is disabled during the HALT mode. However, the clock monitor circuitry if enabled remains active and will cause the WatchDog output pin (WDOUT) to go low. If the HALT mode is used and the user does not want to activate the WDOUT pin, the Clock Monitor should be disabled after the device comes out of reset (resetting the Clock Monitor control bit with the first write to the WDSVR register). In the HALT mode, the power requirements of the device are minimal and the applied voltage (V_{CC}) may be decreased to V_r (V_r = 2.0V) without altering the state of the machine.

The device supports three different ways of exiting the HALT mode. The first method of exiting the HALT mode is with the Multi-Input Wakeup feature on the L port. The second method is with a low to high transition on the CKO (G7) pin. This method precludes the use of the crystal clock configuration (since CKO becomes a dedicated output), and so may be used with an RC clock configuration. The third method of exiting the HALT mode is by pulling the RESET pin low.

Since a crystal or ceramic resonator may be selected as the oscillator, the Wakeup signal is not allowed to start the chip running immediately since crystal oscillators and ceramic resonators have a delayed start up time to reach full amplitude and frequency stability. The IDLE timer is used to generate a fixed delay to ensure that the oscillator has indeed stabilized before allowing instruction execution. In this case, upon detecting a valid Wakeup signal, only the oscillator circuitry is enabled. The IDLE timer is loaded with a value of 256 and is clocked with the te instruction cycle clock. The te clock is derived by dividing the oscillator clock down by a factor of 10. The Schmitt trigger following the CKI inverter on the chip ensures that the IDLE timer is clocked only when the oscillator has a sufficiently large amplitude to meet the Schmitt trigger specifications. This Schmitt trigger is not part of the oscillator closed loop. The startup timeout from the IDLE timer enables the clock signals to be routed to the rest of the chip.

If an RC clock option is being used, the fixed delay is introduced optionally. A control bit, CLKDLY, mapped as configuration bit G7, controls whether the delay is to be introduced or not. The delay is included if CLKDLY is set, and excluded if CLKDLY is reset. The CLKDLY bit is cleared on reset.

The device has two mask options associated with the HALT mode. The first mask option enables the HALT mode feature, while the second mask option disables the HALT mode. With the HALT mode enable mask option, the device will enter and exit the HALT mode as described above. With the HALT disable mask option, the device cannot be placed in the HALT mode (writing a "1" to the HALT flag will have no effect).

The WatchDog detector circuit is inhibited during the HALT mode. However, the clock monitor circuit if enabled remains active during HALT mode in order to ensure a clock monitor error if the device inadvertently enters the HALT mode as a result of a runaway program or power glitch.

IDLE MODE

The device is placed in the IDLE mode by writing a "1" to the IDLE flag (G6 data bit). In this mode, all activity, except the associated on-board oscillator circuitry, the WatchDog logic, the clock monitor and the IDLE Timer T0, is stopped.

As with the HALT mode, the device can be returned to normal operation with a reset, or with a Multi-Input Wakeup from the L Port. Alternately, the microcontroller resumes normal operation from the IDLE mode when the thirteenth bit (representing 4.096 ms at internal clock frequency of 1 MHz, $t_c = 1 \mu s$) of the IDLE Timer toggles.

This toggle condition of the thirteenth bit of the IDLE Timer T0 is latched into the T0PND pending flag.

The user has the option of being interrupted with a transition on the thirteenth bit of the IDLE Timer T0. The interrupt can be enabled or disabled via the T0EN control bit. Setting the T0EN flag enables the interrupt and vice versa.

The user can enter the IDLE mode with the Timer T0 interrupt enabled. In this case, when the T0PND bit gets set, the device will first execute the Timer T0 interrupt service routine and then return to the instruction following the "Enter Idle Mode" instruction.

Alternatively, the user can enter the IDLE mode with the IDLE Timer T0 interrupt disabled. In this case, the device will resume normal operation with the instruction immediately following the "Enter IDLE Mode" instruction.

Note: It is necessary to program two NOP instructions following both the set HALT mode and set IDLE mode instructions. These NOP instructions are necessary to allow clock resynchronization following the HALT or IDLE modes.

Multi-Input Wakeup

The Multi-Input Wakeup feature is used to return (wakeup) the device from either the HALT or IDLE modes. Alternately Multi-Input Wakeup/Interrupt feature may also be used to generate up to 8 edge selectable external interrupts.

Figure 11 shows the Multi-Input Wakeup logic.

The Multi-Input Wakeup feature utilizes the L Port. The user selects which particular L port bit (or combination of L Port bits) will cause the device to exit the HALT or IDLE modes. The selection is done through the Reg: WKEN. The Reg: WKEN is an 8-bit read/write register, which contains a control bit for every L port bit. Setting a particular WKEN bit enables a Wakeup from the associated L port pin.

The user can select whether the trigger condition on the selected L Port pin is going to be either a positive edge (low to high transition) or a negative edge (high to low transition). This selection is made via the Reg: WKEDG, which is an 8-bit control register with a bit assigned to each L Port pin. Setting the control bit will select the trigger condition to be a negative edge on that particular L Port pin. Resetting the bit selects the trigger condition to be a positive edge. Changing an edge select entails several steps in order to avoid a pseudo Wakeup condition as a result of the edge change. First, the associated WKEN bit should be cleared, followed by the associated WKEN bit should be cleared, followed by the associated WKEN bit being re-enabled.

An example may serve to clarify this procedure. Suppose we wish to change the edge select from positive (low going high) to negative (high going low) for L Port bit 5, where bit 5 has previously been enabled for an input interrupt. The program would be as follows:

- RBIT 5, WKEN
- SBIT 5, WKEDG
- RBIT 5, WKPND
- SBIT 5. WKEN

If the L port bits have been used as outputs and then changed to inputs with Multi-Input Wakeup/Interrupt, a safety procedure should also be followed to avoid inherited pseudo wakeup conditions. After the selected L port bits have been changed from output to input but before the associated WKEN bits are enabled, the associated edge select bits in WKEDG should be set or reset for the desired edge selects, followed by the associated WKPND bits being cleared.

This same procedure should be used following reset, since the L port inputs are left floating as a result of reset.

The occurrence of the selected trigger condition for Multi-Input Wakeup is latched into a pending register called WKPND. The respective bits of the WKPND register will be set on the occurrence of the selected trigger edge on the corresponding Port L pin. The user has the responsibility of clearing these pending flags. Since WKPND is a pending register for the occurrence of selected wakeup conditions, the device will not enter the HALT mode if any Wakeup bit is both enabled and pending. Consequently, the user has the responsibility of clearing the pending flags before attempting to enter the HALT mode.

The WKEN, WKPND and WKEDG are all read/write registers, and are cleared at reset.

PORT L INTERRUPTS

Port L provides the user with an additional eight fully selectable, edge sensitive interrupts which are all vectored into the same service subroutine.

The interrupt from Port L shares logic with the wake up circuitry. The register WKEN allows interrupts from Port L to be individually enabled or disabled. The register WKEDG specifies the trigger condition to be either a positive or a negative edge. Finally, the register WKPND latches in the pending trigger conditions.



Multi-Input Wakeup (Continued)

The GIE (global interrupt enable) bit enables the interrupt function. A control flag, LPEN, functions as a global interrupt enable for Port L interrupts. Setting the LPEN flag will enable interrupts and vice versa. A separate global pending flag is not needed since the register WKPND is adequate.

Since Port L is also used for waking the device out of the HALT or IDLE modes, the user can elect to exit the HALT or IDLE modes either with or without the interrupt enabled. If he elects to disable the interrupt, then the device will restart execution from the instruction immediately following the instruction that placed the microcontroller in the HALT or IDLE modes. In the other case, the device will first execute the interrupt service routine and then revert to normal operation.

The Wakeup signal will not start the chip running immediately since crystal oscillators or ceramic resonators have a finite start up time. The IDLE Timer (T0) generates a fixed delay to ensure that the oscillator has indeed stabilized before allowing the device to execute instructions. In this case, upon detecting a valid Wakeup signal, only the oscillator circuitry and the IDLE Timer T0 are enabled. The IDLE Timer is loaded with a value of 256 and is clocked from the tc instruction cycle clock. The tc clock is derived by dividing down the oscillator clock by a factor of 10. A Schmitt trigger following the CKI on-chip inverter ensures that the IDLE timer is clocked only when the oscillator has a sufficiently large amplitude to meet the Schmitt trigger specifications. This Schmitt trigger is not part of the oscillator closed loop. The startup timeout from the IDLE timer enables the clock signals to be routed to the rest of the chip.

If the RC clock option is used, the fixed delay is under software control. A control flag, CLKDLY, in the G7 configuration bit allows the clock start up delay to be optionally inserted. Setting CLKDLY flag high will cause clock start up delay to be inserted and resetting it will exclude the clock start up delay. The CLKDLY flag is cleared during reset, so the clock start up delay is not present following reset with the RC clock options.

A/D Converter

The device contains an 8-channel, multiplexed input, successive approximation, A/D converter. Two dedicated pins, V_{REF} and AGND are provided for voltage reference.

OPERATING MODES

The A/D converter supports ratiometric measurements. It supports both Single Ended and Differential modes of operation.

Four specific analog channel selection modes are supported. These are as follows:

- Allow any specific channel to be selected at one time. The A/D converter performs the specific conversion requested and stops.
- Allow any specific channel to be scanned continuously. In other words, the user will specify the channel and the A/D converter will keep on scanning it continuously. The user can come in at any arbitrary time and immediately read the result of the last conversion. The user does not have to wait for the current conversion to be completed.

Allow any differential channel pair to be selected at one time. The A/D converter performs the specific differential conversion requested and stops.

Allow any differential channel pair to be scanned continuously. In other words, the user will specify the differential channel pair and the A/D converter will keep on scanning it continuously. The user can come in at any arbitrary time and immediately read the result of the last differential conversion. The user does not have to wait for the current conversion to be completed.

The A/D converter is supported by two memory mapped registers, the result register and the mode control register. When the device is reset, the control register is cleared and the A/D is powered down. The A/D result register has unknown data following reset.

A/D Control Register

A control register, Reg: ENAD, contains 3 bits for channel selection, 3 bits for prescaler selection, and 2 bits for mode selection. An A/D conversion is initiated by writing to the ENAD control register. The result of the conversion is available to the user from the A/D result register, Reg: ADRSLT.

Reg: ENAD

CHANNEL SEI		E SELECT	PRESCALER SELE	СТ					
Bits 7, 6, 5	; I	Bits 4,3	Bits 2, 1, 0						
CHANNEL SELECT									
This 3-bit field selects one of eight channels to be the $V_{\rm IN +}$. The mode selection determines the $V_{\rm IN-}$ input.									
Single Ended r	node:								
Bit 7	Bit 6	Bit 5	Channel No.						
0	0	0	0						
0	0	1	1						
0	1	0	2						
0	1	1	Э						
1	0	0	4						
1	n	1	5						

0

1

6

7

1 1 Differential mode: 1

1

Bit 7	Bit 6	Bit 5	Channel Pairs (+)
0	0	0	0, 1
0	0	1	1,0
0	1	0	2, 3
0	1	1	3, 2
1	0	0	4, 5
1	0	1	5, 4
1	1	0	6, 7
1	1	1	7.6

MODE SELECT

This 2-bit field is used to select the mode of operation (single conversion, continuous conversions, differential, single ended) as shown in the following table.

Bit 4	Bit 3	Mode
0	0	Single Ended mode, single conversion
0	1 😐	Single Ended mode, continuous scan of a single channel into the result register
1	0	Differential mode, single conversion
1	1	Differential mode, continuous scan of a channel pair into the result register

A/D Converter (Continued)

PRESCALER SELECT

This 3-bit field is used to select one of the seven prescaler clocks for the A/D converter. The prescaler also allows the A/D clock inhibit power saving mode to be selected. The following table shows the various prescaler options.

Bit 2	Bit 1	Bit 0	Clock Select
0	0	0	Inhibit A/D clock
0	0	1	Divide by 1
0	1	0	Divide by 2
0	1	1	Divide by 4
1	0	0	Divide by 6
1	0	1	Divide by 12
1	1	0	Divide by 8
1	1	1	Divide by 16

ADC Operation

The A/D converter interface works as follows. Writing to the A/D control register ENAD initiates an A/D conversion unless the prescaler value is set to 0, in which case the ADC clock is stopped and the ADC is powered down. The conversion sequence starts at the beginning of the write to ENAD operation powering up the ADC. At the first falling edge of the converter clock following the write operation (not counting the falling edge if it occurs at the same time as the write operation ends), the sample signal turns on for two clock cycles. The ADC is selected in the middle of the sample period. If the ADC is in single conversion mode, the conversion complete signal from the ADC will generate a power down for the A/D converter. If the ADC is in continuous mode, the conversion complete signal will restart the conversion sequence by deselecting the ADC for one converter clock cycle before starting the next sample. The ADC 8-bit result is loaded into the A/D result register (ADRSLT) except during LOAD clock high, which prevents transient data (resulting from the ADC writing a new result over an old one) being read from ADRSLT.

PRESCALER

The A/D Converter (ADC) contains a prescaler option which allows seven different clock selections. The A/D clock frequency is equal to CKI divided by the prescaler value. Note that the prescaler value must be chosen such that the A/D clock falls within the specified range. The maximum A/D frequency is 1.67 MHz. This equates to a 600 ns ADC clock cycle. The A/D converter takes 12 ADC clock cycles to complete a conversion. Thus the minimum ADC conversion time for the device is 7.2 μ s when a prescaler of 6 has been selected. These 12 ADC clock cycles necessary for a conversion consist of 1 cycle at the beginning for reset, 2 cycles for sampling, 8 cycles for converting, and 1 cycle for loading the result into the A/D result register (ADRSLT). This A/D result register is a read-only register. The device cannot write into ADRSLT.

The prescaler also allows an A/D clock inhibit option, which saves power by powering down the A/D when it is not in use.

Note: The A/D converter is also powered down when the device is in either the HALT or IDLE modes. If the ADC is running when the device enters the HALT or IDLE modes, the ADC will power down during the HALT or IDLE, and then will reinitialize the conversion when the device comes out of the HALT or IDLE modes.

Analog Input and Source Resistance Considerations

Figure 12 shows the A/D pin model in single ended mode. The differential mode has similiar A/D pin model. The leads to the analog inputs should be kept as short as possible. Both noise and digital clock coupling to an A/D input can cause conversion errors. The clock lead should be kept away from the analog input line to reduce coupling. The A/D channel input pins do not have any internal output driver circuitry connected to them because this circuitry would load the analog input signals due to output buffer leakage current.

Source impedances greater than 1 k Ω on the analog input lines will adversely affect internal RC charging time during input sampling. As shown in *Figure 12*, the analog switch to the DAC array is closed only during the 2 A/D cycle sample time. Large source impedances on the analog inputs may result in the DAC array not being charged to the correct voltage levels, causing scale errors.

If large source resistance is necessary, the recommended solution is to slow down the A/D clock speed in proportion to the source resistance. The A/D converter may be operated at the maximum speed for R_S less than 1 k Ω . For R_S greater than 1 k Ω , A/D clock speed needs to be reduced. For example, with $R_S = 2 k\Omega$, the A/D converter may be operated at half the maximum speed. A/D converter clock speed may be slowed down by either increasing the A/D prescaler divide-by or decreasing the CKI clock frequency. The A/D clock speed may be reduced to its minimum frequency of 100 kHz.





FIGURE 12. A/D Pin Model (Single Ended Mode)

Interrupts

The device supports a vectored interrupt scheme. It supports a total of ten interrupt sources. The following table lists all the possible interrupt sources, their arbitration ranking and the memory locations reserved for the interrupt vector for each source.

Two bytes of program memory space are reserved for each interrupt source. All interrupt sources except the software interrupt are maskable. Each of the maskable interrupts have an Enable bit and a Pending bit. A maskable interrupt is active if its associated enable and pending bits are set. If GIE = 1 and an interrupt is active, then the processor will be interrupted as soon as it is ready to start executing an instruction except if the above conditions happen during the Software Trap sub-section.

The interruption process is accomplished with the INTR instruction (opcode 00), which is jammed inside the Instruction Register and replaces the opcode about to be executed. The following steps are performed for every interrupt:

- 1. The GIE (Global Interrupt Enable) bit is reset.
- The address of the instruction about to be executed is pushed into the stack.
- The PC (Program Counter) branches to address 00FF. This procedure takes 7 t_c cycles to execute.

At this time, since GIE = 0, other maskable interrupts are disabled. The user is now free to do whatever context switching is required by saving the context of the machine in the stack with PUSH instructions. The user would then program a VIS (Vector Interrupt Select) instruction in order to branch to the interrupt service routine of the highest priority interrupt enabled and pending at the time of the VIS. Note that this is not necessarily the interrupt that caused the branch to address location 00FF Hex prior to the context switching.

Thus, if an interrupt with a higher rank than the one which caused the interruption becomes active before the decision of which interrupt to service is made by the VIS, then the interrupt with the higher rank will override any lower ones and will be acknowledged. The lower priority interrupt(s) are still pending, however, and will cause another interrupt is mediately following the completion of the interrupt service routine associated with the higher priority interrupt just serviced. This lower priority interrupt will occur immediately following the RETI (Return from Interrupt) instruction at the end of the interrupt service routine just completed.

Inside the interrupt service routine, the associated pending bit has to be cleared by software. The RETI (Return from Interrupt) instruction at the end of the interrupt service routine will set the GIE (Global Interrupt Enable) bit, allowing the processor to be interrupted again if another interrupt is active and pending.

The VIS instruction looks at all the active interrupts at the time it is executed and performs an indirect jump to the beginning of the service routine of the one with the highest rank.

The addresses of the different interrupt service routines, called vectors, are chosen by the user and stored in ROM in a table starting at 01E0 (assuming that VIS is located between 00FF and 01DF). The vectors are 15-bit wide and therefore occupy 2 ROM locations.

VIS and the vector table must be located in the same 256byte block (0y00 to 0yFF) except if VIS is located at the last address of a block. In this case, the table must be in the next block. The vector table cannot be inserted in the first 256-byte block.

The vector of the maskable interrupt with the lowest rank is located at 0yE0 (Hi-Order byte) and 0yE1 (Lo-Order byte) and so forth in increasing rank number. The vector of the

Arbitration Ranking	Source	Description	Vector Address HI-Low Byte
(1) Highest	Software	INTR Instruction	0yFE-0yFF
	Reserved	for Future Use	0yFC-0yFD
(2)	External	Pin G0 Edge	0yFA-0yFB
(3)	Timer T0	Underflow	0yF8-0yF9
(4)	Timer T1	T1A/Underflow	0yF6-0yF7
(5)	Timer T1	T1B	0yF4-0yF5
(6)	MICROWIRE/PLUS	BUSY Goes Low	0yF2-0yF3
	Reserved	for Future Use	0yF0-0yF1
	Reserved	for UART	OyEE-OyEF
	Reserved	for UART	0yEC-0yED
(7)	Timer T2	T2A/Underflow	0yEA-0yEB
(8)	Timer T2	T2B	OyE8-OyE9
	Reserved	for Future Use	0yE6-0yE7
	Reserved	for Future Use	0yE4-0yE5
(9)	Port L/Wakeup	Port L Edge	0yE2-0yE3
(10) Lowest	Default	VIS Instr. Execution without Any Interrupts	OyE0-0yE1

y is VIS page, $y \neq 0$



maskable interrupt with the highest rank is located at 0yFA (Hi-Order byte) and 0yFB (Lo-Order byte).

The Software Trap has the highest rank and its vector is located at 0yFE and 0yFF.

If, by accident, a VIS gets executed and no interrupt is active, then the PC (Program Counter) will branch to a vector located at 0yE0-0yE1. This vector can point to the Software Trap (ST) interrupt service routine, or to another special service routine as desired.

Figure 13 shows the Interrupt block diagram.

SOFTWARE TRAP

The Software Trap (ST) is a special kind of non-maskable interrupt which occurs when the INTR instruction (used to acknowledge interrupts) is fetched from ROM and placed inside the instruction register. This may happen when the PC is pointing beyond the available ROM address space or when the stack is over-popped.

When an ST occurs, the user can re-initialize the stack pointer and do a recovery procedure (similar to RESET, but not necessarily containing all of the same initialization procedures) before restarting.

The occurrence of an ST is latched into the ST pending bit. The GIE bit is not affected and the ST pending bit (not accessible by the user) is used to inhibit other interrupts and to direct the program to the ST service routine with the VIS instruction. The RPND instruction is used to clear the software interrupt pending bit. This bit is also cleared on reset.

The ST has the highest rank among all interrupts.

Nothing (except another ST) can interrupt an ST being serviced.

WATCHDOG

The device contains a WATCHDOG and clock monitor. The WATCHDOG is designed to detect the user program getting stuck in infinite loops resulting in loss of program control or "runaway" programs. The Clock Monitor is used to detect

the absence of a clock or a very slow clock below a specified rate on the CKI pin.

The WATCHDOG consists of two independent logic blocks: WD UPPER and WD LOWER. WD UPPER establishes the upper limit on the service window and WD LOWER defines the lower limit of the service window.

Servicing the WATCHDOG consists of writing a specific value to a WATCHDOG Service Register named WDSVR which is memory mapped in the RAM. This value is composed of three fields, consisting of a 2-bit Window Select, a 5-bit Key Data field, and the 1-bit Clock Monitor Select field. Table I shows the WDSVR register.

The lower limit of the service window is fixed at 2048 instruction cycles. Bits 7 and 6 of the WDSVR register allow the user to pick an upper limit of the service window.

Table II shows the four possible combinations of lower and upper limits for the WATCHDOG service window. This flexibility in choosing the WATCHDOG service window prevents any undue burden on the user software.

Bits 5, 4, 3, 2 and 1 of the WDSVR register represent the 5bit Key Data field. The key data is fixed at 01100. Bit 0 of the WDSVR Register is the Clock Monitor Select bit.

TABLE I. WATCHDOG Service Register

Window Select		Key Data				Clock Monitor	
х	X	0	1	1	0	0	Y
7	6	. 5	4	3	2	1	0

TABLE II. WATCHDOG Service Window Select

WDSVR Bit 7	WDSVR Bit 6	Service Window (Lower-Upper Limits)		
0	0	2k-8k t _c Cycles		
0	1	2k-16k t _c Cycles		
° 1	0	2k-32k t _c Cycles		
1	1	2k-64k t _c Cycles		

Clock Monitor

The Clock Monitor aboard the device can be selected or deselected under program control. The Clock Monitor is guaranteed not to reject the clock if the instruction cycle clock ($1/t_c$) is greater or equal to 10 kHz. This equates to a clock input rate on CKI of greater or equal to 100 kHz.

WATCHDOG Operation

The WATCHDOG and Clock Monitor are disabled during reset. The device comes out of reset with the WATCHDOG armed, the WATCHDOG Window Select (bits 6, 7 of the WDSVR Register) set, and the Clock Monitor bit (bit 0 of the WDSVR Register) enabled. Thus, a Clock Monitor error will occur after coming out of reset, if the instruction cycle clock frequency has not reached a minimum specified value, including the case where the oscillator fails to start.

The WDSVR register can be written to only once after reset and the key data (bits 5 through 1 of the WDSVR Register) must match to be a valid write. This write to the WDSVR register involves two irrevocable choices: (i) the selection of the WATCHDOG service window (ii) enabling or disabling of the Clock Monitor. Hence, the first write to WDSVR Register involves selecting or deselecting the Clock Monitor, select the WATCHDOG service window and match the WATCH-DOG key data. Subsequent writes to the WDSVR register will compare the value being written by the user to the WATCHDOG service window value and the key data (bits 7 through 1) in the WDSVR Register. Table III shows the sequence of events that can occur.

The user must service the WATCHDOG at least once before the upper limit of the service window expires. The WATCHDOG may not be serviced more than once in every lower limit of the service window. The user may service the WATCHDOG as many times as wished in the time period between the lower and upper limits of the service window. The first write to the WDSVR Register is also counted as a WATCHDOG service.

The WATCHDOG has an output pin associated with it. This is the WDOUT pin, on pin 1 of the port G. WDOUT is active low. The WDOUT pin is in the high impedance state in the inactive state. Upon triggering the WATCHDOG, the logic will pull the WDOUT (G1) pin low for an additional 16 t_c -32 t_c cycles after the signal level on WDOUT pin goes below the lower Schmitt trigger threshold. After this delay, the device will stop forcing the WDOUT output low.

The WATCHDOG service window will restart when the WDOUT pin goes high. It is recommended that the user tie the WDOUT pin back to V_{CC} through a resistor in order to pull WDOUT high.

A WATCHDOG service while the WDOUT signal is active will be ignored. The state of the WDOUT pin is not guaranteed on reset, but if it powers up low then the WATCHDOG will time out and WDOUT will enter high impedance state.

The Clock Monitor forces the G1 pin low upon detecting a clock frequency error. The Clock Monitor error will continue until the clock frequency has reached the minimum specified value, after which the G1 output will enter the high impedance TRI-STATE mode following 16 t_c-32 t_c clock cycles. The Clock Monitor generates a continual Clock Monitor error if the oscillator fails to start, or fails to reach the minimum specified frequency. The specification for the Clock Monitor is as follows:

 $1/t_c > 10$ kHz—No clock rejection.

 $1/t_c < 10$ Hz—Guaranteed clock rejection.

WATCHDOG AND CLOCK MONITOR SUMMARY

The following salient points regarding the WATCHDOG and CLOCK MONITOR should be noted:

- Both the WATCHDOG and Clock Monitor detector circuits are inhibited during RESET.
- Following RESET, the WATCHDOG and CLOCK MONI-TOR are both enabled, with the WATCHDOG having the maximum service window selected.
- The WATCHDOG service window and Clock Monitor enable/disable option can only be changed once, during the initial WATCHDOG service following RESET.
- The initial WATCHDOG service must match the key data value in the WATCHDOG Service register WDSVR in order to avoid a WATCHDOG error.
- Subsequent WATCHDOG services must match all three data fields in WDSVR in order to avoid WATCHDOG errors.
- The correct key data value cannot be read from the WATCHDOG Service register WDSVR. Any attempt to read this key data value of 01100 from WDSVR will read as key data value of all 0's.
- The WATCHDOG detector circuit is inhibited during both the HALT and IDLE modes.
- The Clock Monitor detector circuit is active during both the HALT and IDLE modes. Consequently, the device inadvertently entering the HALT mode will be detected as a Clock Monitor error (provided that the Clock Monitor enable option has been selected by the program).
- With the single-pin R/C oscillator mask option selected and the CLKDLY bit reset, the WATCHDOG service window will resume following HALT mode from where it left off before entering the HALT mode.

Key Data	Window Data	Clock Monitor	Action
Match	Match	Match	Valid Service: Restart Service Window
Don't Care	Mismatch	Don't Care	Error: Generate WATCHDOG Output
Mismatch	Don't Care	Don't Care	Error: Generate WATCHDOG Output
Don't Care	Don't Care	Mismatch	Error: Generate WATCHDOG Output

TABLE III. WATCHDOG Service Actions

WATCHDOG Operation (Continued)

- With the crystal oscillator mask option selected, or with the single-pin R/C oscillator mask option selected and the CLKDLY bit set, the WATCHDOG service window will be set to its selected value from WDSVR following HALT. Consequently, the WATCHDOG should not be serviced for at least 2048 instruction cycles following HALT, but must be serviced within the selected window to avoid a WATCHDOG error.
- The IDLE timer T0 is not initialized with RESET.
- The user can sync in to the IDLE counter cycle with an IDLE counter (T0) interrupt or by monitoring the T0PND flag. The T0PND flag is set whenever the thirteenth bit of the IDLE counter toggles (every 4096 instruction cycles). The user is responsible for resetting the T0PND flag.
- A hardware WATCHDOG service occurs just as the device exits the IDLE mode. Consequently, the WATCH-DOG should not be serviced for at least 2048 instruction cycles following IDLE, but must be serviced within the selected window to avoid a WATCHDOG error.
- Following RESET, the initial WATCHDOG service (where the service window and the CLOCK MONITOR enable/ disable must be selected) may be programmed anywhere within the maximum service window (65,536 instruction cycles) initialized by RESET. Note that this initial WATCHDOG service may be programmed within the initial 2048 instruction cycles without causing a WATCH-DOG error.

Detection of Illegal Conditions

The device can detect various illegal conditions resulting from coding errors, transient noise, power supply voltage drops, runaway programs, etc.

Reading of undefined ROM gets zeros. The opcode for software interrupt is zero. If the program fetches instructions from undefined ROM, this will force a software interrupt, thus signaling that an illegal condition has occurred.

The subroutine stack grows down for each call (jump to subroutine), interrupt, or PUSH, and grows up for each return or POP. The stack pointer is initialized to RAM location 06F Hex during reset. Consequently, if there are more returns than calls, the stack pointer will point to addresses 070 and 071 Hex (which are undefined RAM). Undefined RAM from addresses 070 to 07F Hex is read as all 1's, which in turn will cause the program to return to address 7FFF Hex. This is an undefined ROM location and the instruction fetched (all 0's) from this location will generate a software interrupt signaling an illegal condition.

Thus, the chip can detect the following illegal conditions:

- a. Executing from undefined ROM
- b. Over "POP"ing the stack by having more returns than calls.

When the software interrupt occurs, the user can re-initialize the stack pointer and do a recovery procedure before restarting (this recovery program is probably similar to that following reset, but might not contain the same program initialization procedures).

MICROWIRE/PLUS

MICROWIRE/PLUS is a serial synchronous communications interface. The MICROWIRE/PLUS capability enables the device to interface with any of National Semiconductor's MICROWIRE peripherals (i.e. A/D converters, display drivers, E²PROMs etc.) and with other microcontrollers which support the MICROWIRE interface. It consists of an 8-bit serial shift register (SIO) with serial data input (SI), serial data output (SO) and serial shift clock (SK). *Figure 14* shows a block diagram of the MICROWIRE/PLUS logic.



FIGURE 14. MICROWIRE/PLUS Block Diagram

The shift clock can be selected from either an internal source or an external source. Operating the MICROWIRE/ PLUS arrangement with the internal clock source is called the Master mode of operation. Similarly, operating the MI-CROWIRE/PLUS arrangement with an external shift clock is called the Slave mode of operation.

The CNTRL register is used to configure and control the MICROWIRE/PLUS mode. To use the MICROWIRE/PLUS, the MSEL bit in the CNTRL register is set to one. In the master mode the SK clock rate is selected by the two bits, SL0 and SL1, in the CNTRL register. TABLE IV details the different clock rates that may be selected.

TABLE IV. MICROWIRE/PLUS Master Mode Clock Selection

SL1	SL0	SK
0	0	$2 \times t_c$
0	1	$4 \times t_c$
1	x	$8 \times t_c$

Where tc is the instruction cycle clock

MICROWIRE/PLUS OPERATION

Setting the BUSY bit in the PSW register causes the MI-CROWIRE/PLUS to start shifting the data. It gets reset when eight data bits have been shifted. The user may reset the BUSY bit by software to allow less than 8 bits to shift. If enabled, an interrupt is generated when eight data bits have been shifted. The device may enter the MICROWIRE/PLUS mode either as a Master or as a Slave. *Figure 15* shows how two COP8880CF microcontrollers and several peripherals may be interconnected using the MICROWIRE/PLUS arrangements.

Warning:

The SIO register should only be loaded when the SK clock is low. Loading the SIO register while the SK clock is high will result in undefined data in the SIO register. SK clock is normally low when not shifting.

Setting the BUSY flag when the input SK clock is high in the MICROWIRE/PLUS slave mode may cause the current SK clock for the SIO shift register to be narrow. For safety, the BUSY flag should only be set when the input SK clock is low.

MICROWIRE/PLUS Master Mode Operation

In the MICROWIRE/PLUS Master mode of operation the shift clock (SK) is generated internally. The MICROWIRE Master always initiates all data exchanges. The MSEL bit in the CNTRL register must be set to enable the SO and SK functions onto the G Port. The SO and SK pins must also be selected as outputs by setting appropriate bits in the Port G configuration register. Table V summarizes the bit settings required for Master mode of operation.



MICROWIRE/PLUS (Continued)

MICROWIRE/PLUS Slave Mode Operation

In the MICROWIRE/PLUS Slave mode of operation the SK clock is generated by an external source. Setting the MSEL bit in the CNTRL register enables the SO and SK functions onto the G Port. The SK pin must be selected as an input and the SO pin is selected as an output pin by setting and resetting the appropriate bit in the Port G configuration register. Table V summarizes the settings required to enter the Slave mode of operation.

The user must set the BUSY flag immediately upon entering the Slave mode. This will ensure that all data bits sent by the Master will be shifted properly. After eight clock pulses the BUSY flag will be cleared and the sequence may be repeated.

Alternate SK Phase Operation

The device allows either the normal SK clock or an alternate phase SK clock to shift data in and out of the SIO register. In both the modes the SK is normally low. In the normal mode data is shifted in on the rising edge of the SK clock and the data is shifted out on the falling edge of the SK clock. The SIO register is shifted on each falling edge of the SK clock in the normal mode. In the alternate SK phase mode the SIO register is shifted on the rising edge of the SK clock.

A control flag, SKSEL, allows either the normal SK clock or the alternate SK clock to be selected. Resetting SKSEL causes the MICROWIRE/PLUS logic to be clocked from the normal SK signal. Setting the SKSEL flag selects the alternate SK clock. The SKSEL is mapped into the G6 configuration bit. The SKSEL flag will power up in the reset condition, selecting the normal SK signal.

TABLE V

This table assumes that the control flag MSEL is set.

G4 (SO) Config. Bit	G5 (SK) Config. Bit	G4 Fun.	G5 Fun.	Operation
1	1	SO	Int. SK	MICROWIRE/PLUS Master
0	1	TRI- STATE	lnt. SK	MICROWIRE/PLUS Master
1	0	SO	Ext. SK	MICROWIRE/PLUS Slave
0	0	TRI- STATE	Ext. SK	MICROWIRE/PLUS Slave

Memory Map

All RAM, ports and registers (except A and PC) are mapped into data memory address space

Address	Contents
00 to 6F	On-Chip RAM bytes
70 to BF	Unused RAM Address Space
C0 C1 C2 C3 C4 C5 C6 C7 C8 C9 CA CB CC CD to CF	Timer T2 Lower Byte Timer T2 Upper Byte Timer T2 Autoload Register T2RA Lower Byte Timer T2 Autoload Register T2RA Upper Byte Timer T2 Autoload Register T2RB Lower Byte Timer T2 Autoload Register T2RB Upper Byte Timer T2 Control Register WATCHDOG Service Register (Reg:WDSVR) MIWU Edge Select Register (Reg:WKEDG) MIWU Enable Register (Reg:WKEN) MIWU Pending Register (Reg:WKEND) A/D Converter Control Register (Reg: ADRSLT) Reserved
D0 D1 D2 D3 D4 D5 D6 D7 D8 D9 DA D9 DA DB DC DD to DF	Port L Data Register Port L Configuration Register Port L Input Pins (Read Only) Reserved for Port L Port G Data Register Port G Configuration Register Port G Input Pins (Read Only) Port I Input Pins (Read Only) Port C Data Register Port C Configuration Register Port C Input Pins (Read Only) Reserved for Port C Port D Data Register Reserved for Port D
E0 to E5 E6 E7 E8 E9 EA EB EC ED EE EF	Reserved Timer T1 Autoload Register T1RB Lower Byte Timer T1 Autoload Register T1RB Upper Byte ICNTRL Register MICROWIRE Shift Register Timer T1 Lower Byte Timer T1 Upper Byte Timer T1 Autoload Register T1RA Lower Byte Timer T1 Autoload Register T1RA Upper Byte CNTRL Control Register PSW Register
F0 to FB FC FD FE FF	On-Chip RAM Mapped as Registers X Register SP Register B Register Reserved

Reading memory locations 70-7F Hex will return all ones. Reading other unused memory locations will return undefined data.

Addressing Modes

The device has ten addressing modes, six for operand addressing and four for transfer of control.

OPERAND ADDRESSING MODES

Register Indirect

This is the "normal" addressing mode. The operand is the data memory addressed by the B pointer or X pointer.

Register Indirect (with auto post increment or decrement of pointer)

This addressing mode is used with the LD and X instructions. The operand is the data memory addressed by the B pointer or X pointer. This is a register indirect mode that automatically post increments or decrements the B or X register after executing the instruction.

Direct

The instruction contains an 8-bit address field that directly points to the data memory for the operand.

Immediate

The instruction contains an 8-bit immediate field as the operand.

Short Immediate

This addressing mode is used with the Load B Immediate instruction. The instruction contains a 4-bit immediate field as the operand.

Indirect

This addressing mode is used with the LAID instruction. The contents of the accumulator are used as a partial address (lower 8 bits of PC) for accessing a data operand from the program memory.

TRANSFER OF CONTROL ADDRESSING MODES

Relative

This mode is used for the JP instruction, with the instruction field being added to the program counter to get the new program location. JP has a range from -31 to +32 to allow a 1-byte relative jump (JP + 1 is implemented by a NOP instruction). There are no "pages" when using JP, since all 15 bits of PC are used.

Absolute

This mode is used with the JMP and JSR instructions, with the instruction field of 12 bits replacing the lower 12 bits of the program counter (PC). This allows jumping to any location in the current 4k program memory segment.

Absolute Long

This mode is used with the JMPL and JSRL instructions, with the instruction field of 15 bits replacing the entire 15 bits of the program counter (PC). This allows jumping to any location in the current 4k program memory space.

Indirect

This mode is used with the JID instruction. The contents of the accumulator are used as a partial address (lower 8 bits of PC) for accessing a location in the program memory. The contents of this program memory location serve as a partial address (lower 8 bits of PC) for the jump to the next instruction.

Note: The VIS is a special case of the Indirect Transfer of Control addressing mode, where the double byte vector associated with the interrupt is transferred from adjacent addresses in the program memory into the program counter (PC) in order to jump to the associated interrupt service routine.

Instruction Set

Register and Symbol Definition

Registers				
Α	8-Bit Accumulator Register			
в	8-Bit Address Register			
х	8-Bit Address Register			
SP	8-Bit Stack Pointer Register			
PC	15-Bit Program Counter Register			
PU	Upper 7 Bits of PC			
PL	Lower 8 Bits of PC			
С	1 Bit of PSW Register for Carry			
HC	1 Bit of PSW Register for Half Carry			
GIE	1 Bit of PSW Register for Global			
	Interrupt Enable			
VU	Interrupt Vector Upper Byte			
VL	Interrupt Vector Lower Byte			

Symbols

=
¥.

instructi	i on Set (C	ontinued)	
NSTRUCTIO	N SET		
ADD ADC	A,Meml A,Meml	ADD ADD with Carry	$\begin{array}{l} A A + Meml \\ A A + Meml + C, C Carry \end{array}$
SUBC	A,Meml	Subtract with Carry	HC ← Half Carry A ← A Memi + C, C ← Carry HC ← Half Carry
AND	A,Meml	Logical AND	A - A and Memi
ANUSZ	A,imm	Logical AND Immed., Skip if Zero	Skip next ir (A and imm) = 0
	A,Memi	Logical OR	
	MD Imm		Compare MD and Imm Do next if MD == Imm
	A Memi	IF FOual	Compare A and Memi. Do next if A = Memi
IFNE	A Memi	IF Not Equal	Compare A and Memi, Do next if $A \neq Memi$
IFGT	A.Meml	IF Greater Than	Compare A and Memi, Do next if A > Memi
IFBNE	#	If B Not Equal	Do next if lower 4 bits of $B \neq Imm$
DRSZ	Req	Decrement Reg., Skip if Zero	Reg - Reg - 1, Skip if Reg = 0
SBIT	#,Mem	Set BIT	1 to bit, Mem (bit = 0 to 7 immediate)
RBIT	#,Mem	Reset BIT	0 to bit, Mem
IFBIT	#,Mem	IF BIT	If bit in A or Mem is true do next instruction
RPND		Reset PeNDing Flag	Reset Software Interrupt Pending Flag
x	A,Mem	EXchange A with Memory	A ↔ Mem
х	A,[X]	EXchange A with Memory [X]	A ←→ [X]
LD	A,Meml	LoaD A with Memory	A ← Memi
LD	A,[X]	LoaD A with Memory [X]	A ← [X]
LD	B,Imm	LoaD B with Immed.	B ← Imm
	Mem,Imm	LoaD Memory Immed	
	Reg,imm	LoaD Register Memory Immed.	Reg imm
X	A, [B ±]	EXchange A with Memory [B]	$A \longleftrightarrow [B], (B \leftarrow B \pm 1)$
x	A, [X ±]	Exchange A with Memory [X]	$A \longleftrightarrow [X], (X \leftarrow \pm 1)$
		LoaD A with Memory [B]	$A \leftarrow [B], (B \leftarrow B \pm I)$
	(B+1.1mm	LoaD Memory [B] Immed.	$[B] \leftarrow Imm (B \leftarrow B+1)$
	A		
INC	Â	INCrement A	$A \leftarrow A + 1$
DEC	Â	DECrementA	A ← A − 1
LAID		Load A InDirect from ROM	A - ROM (PU,A)
DCOR	Α	Decimal CORrect A	A ← BCD correction of A (follows ADC, SUBC)
RRC	A	Rotate A Right thru C	$C \rightarrow A7 \rightarrow \ldots \rightarrow A0 \rightarrow C$
RLC	A	Rotate A Left thru C	$C \leftarrow A7 \leftarrow \dots \leftarrow A0 \leftarrow C$
SWAP	Α	SWAP nibbles of A	A7A4 ↔ A3A0
SC		Set C	$C \leftarrow 1, HC \leftarrow 1$
HC		Reset C	C - 0, HC - 0
		IF C IE Not C	If C is not true, do next instruction
POP	А	POP the stack into A	$SP \leftarrow SP + 1 A \leftarrow [SP]$
PUSH	Â	PUSH A onto the stack	$[SP] \leftarrow A, SP \leftarrow SP - 1$
VIS		Vector to Interrupt Service Routine	PU ← [VU].PL ← [VL]
JMPL	Addr.	Jump absolute Long	PC ← ii (ii = 15 bits, 0 to 32k)
JMP	Addr.	Jump absolute	$PC90 \leftarrow i (i = 12 \text{ bits})$
JP	Disp.	Jump relative short	PC \leftarrow PC + r (r is -31 to +32, except 1)
JSRL	Addr.	Jump SubRoutine Long	$[SP] \leftarrow PL, [SP-1] \leftarrow PU, SP-2, PC \leftarrow ii$
JSR	Addr	Jump SubRoutine	$[SP] \leftarrow PL, [SP-1] \leftarrow PU, SP-2, PC90 \leftarrow i$
JID		Jump InDirect	PL ← ROM (PU,A)
HEI			$\begin{vmatrix} ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST], TU \leftarrow [ST-1] \\ ST + 2, TL \leftarrow [ST-1] \\ ST + 2,$
REISK		RETurn from Interrupt	$SP + 2 PI \leftarrow [SP] PI \leftarrow [SP - 1]$
INTR		Generate an Interrupt	$[SP] \leftarrow PL, [SP-1] \leftarrow PL, SP-2, PC \leftarrow OFF$
NOP		No OPeration	$PC \leftarrow PC + 1$
			۱d

Instruction Execution Time

Most instructions are single byte (with immediate addressing mode instructions taking two bytes).

Most single byte instructions take one cycle time to execute. See the BYTES and CYCLES per INSTRUCTION table for details.

Bytes and Cycles per Instruction

The following table shows the number of bytes and cycles for each instruction in the format of byte/cycle.

Arithmetic ar	nd Logic	Instructions
---------------	----------	--------------

	[B]	Direct	Immed.
ADD	1/1	3/4	2/2
ADC	1/1	3/4	2/2
SUBC	1/1	3/4	2/2
AND	1/1	3/4	2/2
OR	1/1	3/4	2/2
XOR	1/1	3/4	2/2
IFEQ	1/1	3/4	2/2
IFNE	1/1	3/4	2/2
IFGT	1/1	3/4	2/2
IFBNE	1/1		
DRSZ		1/3	
SBIT	1/1	3/4	
RBIT	1/1	3/4	
IFBIT	1/1	3/4	

Instructions Using A & C					
CLRA	1/1				
INCA	1/1				
DECA	1/1				
LAID	1/3				
DCOR	1/1				
RRCA	1/1				
RLCA	1/1				
SWAPA	1/1				
SC	1/1				
RC	1/1				
IFC	1/1				
IFNC	1/1				
PUSHA	1/3				
POPA	1/3				
ANDSZ	2/2				

Transfer of Control Instructions					
JMPL	3/4				
JMP	2/3				
JP	1/3				
JSRL	3/5				
JSR	2/5				
JID	1/3				
VIS	1/5				
RET	1/5				
RETSK	1/5				
RETI	1/5				
INTR	1/7				
NOP	1/1				

RPND

1/1

Memory Transfer Instructions

	Register Indirect		Direct	Immed.	Register Indirect Auto Incr. & Decr.		
	[H]	[X]			[B+,B-]	[X+, X-]	
X A,*	1/1	1/3	2/3		1/2	1/3	
LD A,*	1/1	1/3	2/3	2/2	1/2	1/3	
LD B, Imm			1	1/1			(IF B < 16)
LD B, Imm			ļ	2/2			(IF B > 15)
LD Mem, Imm	2/2		3/3		2/2		
LD Reg, Imm			2/3				
IFEQ MD, Imm			3/3				

* = > Memory location addressed by B or X or directly.

Opcode Table Upper Nibble Along X-Axis

Lower Nibble Along Y-Axis

F	E	D	C ver	В	A	9	8	
JP – 15	JP31	LD 0F0, # i	DRSZ 0F0	RRCA	RC	ADC A,#i	ADC A,[B]	0
JP 14	JP -30	LD 0F1, # i	DRSZ 0F1	•	SC	SUBC A, #i	SUB A,[B]	1
JP - 13	JP - 29	LD 0F2, # i	DRSZ 0F2	X A, [X+]	X A,[B+]	IFEQ A, #i	IFEQ A,[B]	2
JP - 12	JP 28	LD 0F3, # i	DRSZ 0F3	X A, [X –]	X A,[B-]	IFGT A,#i	IFGT A,[B]	3
JP 11	JP - 27	LD 0F4, # i	DRSZ 0F4	VIS	LAID	ADD A,#i	ADD A,[B]	4
JP – 10	JP - 26	LD 0F5, # i	DRSZ 0F5	RPND	JID	AND A, #i	AND A,[B]	5
JP - 9	JP -25	LD 0F6, # i	DRSZ 0F6	X A,[X]	X A,[B]	XOR A, #i	XOR A,[B]	6
JP -8	JP24	LD 0F7, # i	DRSZ 0F7	•	•	OR A, #i	OR A,[B]	7
JP - 7	JP -23	LD 0F8, # i	DRSZ 0F8	NOP	RLCA	LD A, #i	IFC	8
JP -6	JP - 22	LD 0F9, <i>#</i> i	DRSZ 0F9	IFNE A,[B]	IFEQ Md,#i	IFNE A,#i	IFNC	9
JP - 5	JP -21	LD 0FA, # i	DRSZ 0FA	LD A,[X+]	LD A,[B+]	LD [B+],#i	INCA	A
JP -4	JP - 20	LD 0FB, # i	DRSZ 0FB	LD A,[X-]	LD A,[B-]	LD [B-],#i	DECA	в
JP -3	JP – 19	LD 0FC, # i	DRSZ OFC	LD Md, #i	JMPL	X A,Md	POPA	с
JP -2	JP – 18	LD 0FD, # i	DRSZ OFD	DIR	JSRL	LD A,Md	RETSK	D
JP 1	JP – 17	LD 0FE, # i	DRSZ OFE	LD A,[X]	LD A,[B]	LD [B],#i	RET	E
JP -0	JP – 16	LD 0FF, # i	DRSZ 0FF	•	•	LD B, #i	RETI	F

Opcode Table (Continued)

Upper Nibble Along X-Axis Lower Nibble Along Y-Axis

7	6	5	4	3	2	1	0	
IFBIT 0,[B]	ANDSZ A, #i	LD B, #0F	IFBNE 0	JSR x000-x0FF	JMP x000-x0FF	JP +17	INTR	0
IFBIT 1,[B]	•	LD B, #0E	IFBNE 1	JSR x100-x1FF	JMP x100-x1FF	JP +18	JP + 2	1
IFBIT 2,[B]	•	LD B, #0D	IFBNE 2	JSR x200-x2FF	JMP x200-x2FF	JP +19	JP + 3	2
IFBIT 3,[B]	•	LD B, #0C	IFBNE 3	JSR x300-x3FF	JMP x300-x3FF	JP +20	JP + 4	З
IFBIT 4,[B]	CLRA	LD B, #0B	IFBNE 4	JSR x400-x4FF	JMP x400-x4FF	JP +21	JP + 5	4
IFBIT 5,[B]	SWAPA	LD B, #0A	IFBNE 5	JSR x500-x5FF	JMP x500-x5FF	JP + 22	JP + 6	5
IFBIT 6,[B]	DCORA	LD B, #09	IFBNE 6	JSR x600-x6FF	JMP x600-x6FF	JP +23	JP + 7	6
IFBIT 7,[B]	PUSHA	LD B, #08	IFBNE 7	JSR x700-x7FF	JMP x700-x7FF	JP + 24	JP + 8	7
SBIT 0,[B]	RBIT 0.[B]	LD B, #07	IFBNE 8	JSR x800-x8FF	JMP x800-x8FF	JP + 25	JP + 9	8
SBIT 1,[B]	RBIT 1,[B]	LD B, #06	IFBNE 9	JSR x900-x9FF	JMP x900-x9FF	JP +26	JP + 10	9
SBIT 2,[B]	RBIT 2,[B]	LD B, #05	IFBNE 0A	JSR xA00-xAFF	JMP xA00-xAFF	JP + 27	JP + 11	A
SBIT 3,[B]	RBIT 3,[B]	LD B, #04	IFBNE 0B	JSR xB00-xBFF	JMP xB00-xBFF	JP + 28	JP + 12	В
SBIT 4,[B]	RBIT 4,[B]	LD B, #03	IFBNE 0C	JSR xC00-xCFF	JMP xC00-xCFF	JP + 29	JP + 13	С
SBIT 5,[B]	RBIT 5,[B]	LD B, #02	IFBNE 0D	JSR xD00-xDFF	JMP xD00-xDFF	JP + 30	JP + 14	D
SBIT 6,[B]	RBIT 6,[B]	LD B, #01	IFBNE 0E	JSR xE00-xEFF	JMP xE00-xEFF	JP +31	JP + 15	E
SBIT 7,[B]	RBIT 7,[B]	LD B,#00	IFBNE OF	JSR xF00-xFFF	JMP xF00-xFFF	JP +32	JP + 16	F

Where,

i is the immediate data Md is a directly addressed memory location

* is an unused opcode

Note: The opcode 60 Hex is also the opcode for IFBIT #i,A

Mask Options

The mask programmable options are shown below. The options are programmed at the same time as the ROM pattern submission.

OPTION	1:	CLOCK	CONFIGURATION

- = 1 Crystal Oscillator (CKI/10) G7 (CKO) is clock generator output to crystal/resonator CKI is the clock input
- = 2 Single-pin RC controlled oscillator (CKI/10)

G7 is available as a HALT restart and/or general purpose input

- OPTION 2: HALT
 - = 1 Enable HALT mode
 - = 2 Disable HALT mode
- OPTION 3: BONDING
 - = 1 44-Pin PLCC
 - = 2 40-Pin DIP
 - = 3 N/A
 - = 4 28-Pin DIP
 - = 5 28-Pin S0

Development Support

IN-CIRCUIT EMULATOR

The MetaLink iceMASTERTM-COP8 Model 400 In-Circuit Emulator for the COP8 family of microcontrollers features high-performance operation, ease of use, and an extremely flexible user-interface or maximum productivity. Interchangeable probe cards, which connect to the standard common base, support the various configurations and packages of the COP8 family.

The iceMASTER provides real time, full speed emulation up to 10 MHz, 32 kBytes of emulation memory and 4k frames of trace buffer memory. The user may define as many as 32k trace and break triggers which can be enabled, disabled, set or cleared. They can be simple triggers based on code address, direct address, opcode value, opcode class or immediate operand. Complex breakpoints can be ANDed and ORed together. Trace information consists of address bus values, opcodes and user selectable probe clips status (external event lines). The trace buffer can be viewed as raw hex or as disassembled instructions. The probe clip bit values can be displayed in binary, hex or digital waveform formats.

During single-step operation the dynamically annotated code feature displays the contents of all accessed (read and write) memory locations and registers, as well as flow-of-control direction change markers next to each instruction executed.

The iceMASTER's performance analyzer offers a resolution of better than 6 μs . The user can easily monitor the time spent executing specific portions of code and find 'hot spots'' or 'dead code''. Up to 15 independent memory areas based on code address or label ranges can be defined. Analysis results can be viewed in bar graph format or as actual frequency count.

Emulator memory operations for program memory include single line assembler, disassembler, view, change and write to file. Data memory operations include fill, move, compare, dump to file, examine and modify. The contents of any memory space can be directly viewed and modified from the corresponding window.

The iceMASTER comes with an easy to use window interface. Each window can be sized, highlighted, color-controlled, added, or removed completely. Commands can be accessed via pull-down-menus and/or redefinable hot keys. A context sensitive hypertext/hyperlinked on-line help system explains clearly the options the user has from within any window.

The iceMASTER connects easily to a PC[®] via the standard COMM port and its 115.2 kBaud serial link keeps typical program download time to under 3 seconds.

The following tables list the emulator and probe cards ordering information.

Part Number	Description	Current Version
IM-COP8/400/1‡	MetaLink base unit in-circuit emulator for all COP8 devices, symbolic debugger software and RS-232 serial interface cable, with 110V @ 60 Hz Power Supply.	
IM-COP8/400/2‡	MetaLink base unit in-circuit emulator for all COP8 devices, symbolic debugger software and RS-232 serial interface cable, with 220V @ 50 Hz Power Supply.	HOST SOFTWARE: VER. 3.3 REV.5,
DM-COP8/888CF‡	MetaLink iceMASTER Debug Module. This is the low cost version of MetaLink's iceMASTER. Firmware: Ver. 6.07.	Model File Rev 3.050.

Emulator Ordering Information

Development Support (Continued)

Part Number	Package	Voltage Range	Emulates
MHW-884CF28D5PC	28 DIP	4.5V-5.5V	COP884CF
MHW-884CF28DWPC	28 DIP	2.5V-6.0V	COP884CF
MHW-888CF40D5PC	40 DIP	4.5V-5.5V	COP888CF
MHW-888CF40DWPC	40 DIP	2.5V-6.0V	COP888CF
MWH-888CF44D5PC	44 PLCC	4.5V-5.5V	COP888CF
MHW-888CF44DWPC	44 PLCC	2.5V-6.0V	COP888CF

MACRO CROSS ASSEMBLER

National Semiconductor offers a COP8 macro cross assembler. It runs on industry standard compatible PCs and supports all of the full-symbolic debugging features of the MetaLink iceMASTER emulators.

Assembler Ordering Information

Part Number	Description	Manual
COP8-DEV-IBMA	COP8 Assembler/ Linker/Librarian for IBM®, PC/XT®, AT® or compatible.	424410632-001

SINGLE CHIP EMULATOR DEVICE

The COP8 family is fully supported by One-Time Programmable (OTP) emulators. For more detailed information refer to the emulation device specific datasheets and the emulator selection table below.

PROGRAMMING SUPPORT

Programming of the single chip emulator devices is supported by different sources. The following programmers are certified for programming the One-Time Programmable (OTP) devices.

Manufacturer and Product	U.S. Nเ	Phone Imber	Euro	ppe Phone lumber	Asia Phone Number		
MetaLink-Debug Module	(602) 926-0797		Germany: +49-8141-1030		Hong Kong: +852-737-1800		
Zeltek-Superpro	(408) 7	45-7974	Germany: + 49-20-41 684758		Singapore: +65 276 6433		
BP Microsystems-EP-1140	(800) 2	25-2102	Germany: +49-89 857 66 67		Hong Kong: +852 388 0629		
Data I/O-Unisite; -System 29, -System 39	(800) 322-8246		Europe: + 31-20-622866 Germany: + 49-89-85-8020		Japan: +33-432-6991		
Abcom-COP8 Programmer		<u> </u>	Europe: + 89-80 8707				
System General Turpro-1-FX; -APRO	(408) 2	63-6667	Switzerland: +31-921-7844		Taiwan Taipei: +2-9173005		
OTP Emulator Ordering Information							
Device Number	er Clock Option			Package	Emulates		
COP8788CFV-X COP8788CFV-R*		Crystal R/C		44 LDCC	COP888CF		

EPROM Programmer Information

Device Number	Clock Option	Раскаде	Emulates
COP8788CFV-X COP8788CFV-R*	Crystal R/C	44 LDCC	COP888CF
COP8788CFN-X COP8788CFN-R*	Crystal R/C	40 DIP	COP888CF
COP8784CFN-X COP8784CFN-R•	Crystal R/C	28 DIP	COP884CF
COP8784CFWM-X* COP8784CFWM-R*	Crystal R/C	28 SO	COP884CF

*Check with the local sales office about the availability.

Development Support (Continued) DIAL-A-HELPER

Dial-A-Helper is a service provided by the Microcontroller Applications group. The Dial-A-Helper is an Electronic Bulletin Board Information system.

INFORMATION SYSTEM

The Dial-A-Helper system provides access to an automated information storage and retrieval system that may be accessed over standard dial-up telephone lines 24 hours a day. The system capabilities include a MESSAGE SECTION (electronic mail) for communications to and from the Microcontroller Applications Group and a FILE SECTION which consists of several file areas where valuable application software and utilities could be found. The minimum requirement for accessing the Dial-A-Helper is a Hayes compatible modem.

If the user has a PC with a communications package then files from the FILE SECTION can be down loaded to disk for later use.

ORDER P/N: MOLE-DIAL-A-HLP

Information System Package Contents: Dial-A-Helper Users Manual Public Domain Communications Software

FACTORY APPLICATIONS SUPPORT

Dial-A-Helper also provides immediate factor applications support. If a user has questions, he can leave messages on our electronic bulletin board, which we will respond to.

Voice:	(800) 272-9959	
Modem:	Canada/	
	U.S.:	(800) NSC-MICRO
		(800) 672-6427
	Baud:	14.4k
	Set-Up:	Length: 8-Bit Parity: None Stop Bit: 1
	Operation:	24 Hours, 7 Days