# DIGITAL 8000 SERIES TTL/MSI


## **DESCRIPTION**

The 8269, a 4 BIT COMPARATOR, is an array of gates designed to perform the numerical comparison of two four-bit binary numbers. The outputs indicate whether the two numbers are equal in value, or which number is the greater. The 8269 is a functional and pin-for-pin replacement for the DM8200.

# TRUTH TABLE

		INPU	OUT	OUTPUT		
An		Bn	STROBE	х	Υ	
A	` >	В	0	1	0	
A	<	В	0	0	1	
Α	. =	В	0	1	1	
Α Α	_ ≨	В	1	0	0	

## **LOGIC DIAGRAM**



# **ELECTRICAL CHARACTERISTICS** (Over Recommended Operating Temperature And Voltage)

	LIMITS				TEST CONDITIONS	
CHARACTERISTICS	MIN.	TYP.	MAX.	UNITS	TEST CONDITIONS	
"1" Output Voltage	2.6	3.5		v	l <sub>out</sub> = 800μA	
"0" Output Voltage		0.2	0.4	v	I <sub>out</sub> = 16mA	
"1" Input Current			80	μΑ	V <sub>in</sub> = 4.5V	
"0" Input Current	- 0.1		-3.2	mA	V <sub>in</sub> = 0.4V	
Power Consumption	1		278/53	mW/mA	V <sub>CC</sub> = 5.25V	
Short Circuit Output Current	- 18		- 55	mA	$V_{out} = 0V, V_{CC} = 5.25V$	
Input Latch Voltage	5.5		}	v	l <sub>out</sub> = 10mA	

# $T_A = 25^{\circ} C$ and $V_{CC} = 5.0 V$

	LIMITS				
CHARACTERISTICS	MIN.	TYP.	MAX.	UNITS	TEST CONDITIONS
Propagation Delay			_		
tpd1 (Data Input to Output)			40	ns	Test Figure 1
tpd0 (Data Input to Output)			30	ns	Test Figure 1
tpd1 (Strobe to Output)			27	ns	Test Figure 2
tpd0 (Strobe to Output)		1	18	ns	Test Figure 2

## SIGNETICS DIGITAL 8000 SERIES TTL/MSI - 8269

#### NOTES:

- All voltage and capacitance measurements are referenced to the ground terminal.
  - Terminals not specifically referenced are left electrically open.
- 2. All measurements are taken with ground pin tied to zero volts.
- 3. Positive current flow is defined as into the terminal referenced.
- 4. Positive logic definition: "UP" Level = "1", "DOWN" Level = "0".
- Precautionary measures should be taken to ensure current limiting in accordance with Absolute Maximum Ratings should the isolation diodes become forward biased.
- 6. Output source current is supplied through a resistor to ground.
- 7. Output sink current is supplied through a resistor to V<sub>CC</sub>.
- 8. Manufacturer reserves the right to make design and process changes and improvements.

## **AC TEST FIGURE AND WAVEFORMS**

